
Up to 6 GHz Medium Power Silicon Bipolar Transistor

Technical Data

AT-42070

Features

- **High Output Power:**
21.0 dBm Typical $P_{1\text{ dB}}$ at 2.0 GHz
20.5 dBm Typical $P_{1\text{ dB}}$ at 4.0 GHz
- **High Gain at 1 dB
Compression:**
15.0 dB Typical $G_{1\text{ dB}}$ at 2.0 GHz
10.0 dB Typical $G_{1\text{ dB}}$ at 4.0 GHz
- **Low Noise Figure:**
1.9 dB Typical NF_O at 2.0 GHz
- **High Gain-Bandwidth
Product:** 8.0 GHz Typical f_T
- **Hermetic Gold-ceramic
Microstrip Package**


Description

Hewlett-Packard's AT-42070 is a general purpose NPN bipolar transistor that offers excellent high frequency performance. The AT-42070 is housed in a hermetic, high reliability gold-ceramic 70 mil microstrip package. The 4 micron emitter-to-emitter pitch enables this transistor to be used in many

different functions. The 20 emitter finger interdigitated geometry yields a medium sized transistor with impedances that are easy to match for low noise and medium power applications. This device is designed for use in low noise, wideband amplifier, mixer and oscillator applications in the VHF, UHF, and microwave frequencies. An optimum noise match near $50\ \Omega$ up to 1 GHz, makes this device easy to use as a low noise amplifier.

The AT-42070 bipolar transistor is fabricated using Hewlett-Packard's 10 GHz f_T Self-Aligned-Transistor (SAT) process. The die is nitride passivated for surface protection. Excellent device uniformity, performance and reliability are produced by the use of ion-implantation, self-alignment techniques, and gold metalization in the fabrication of this device.

70 mil Package



AT-42070 Absolute Maximum Ratings

Symbol	Parameter	Units	Absolute Maximum ^[1]
V_{EBO}	Emitter-Base Voltage	V	1.5
V_{CBO}	Collector-Base Voltage	V	20
V_{CEO}	Collector-Emitter Voltage	V	12
I_C	Collector Current	mA	80
P_T	Power Dissipation ^[2,3]	mW	600
T_j	Junction Temperature	°C	200
T_{STG}	Storage Temperature	°C	-65 to 200

Thermal Resistance^[2,4]:

$$\theta_{jc} = 150^{\circ}\text{C/W}$$

Notes:

1. Permanent damage may occur if any of these limits are exceeded.
2. $T_{CASE} = 25^{\circ}\text{C}$.
3. Derate at $6.7 \text{ mW/}^{\circ}\text{C}$ for $T_C > 110^{\circ}\text{C}$.
4. The small spot size of this technique results in a higher, though more accurate determination of θ_{jc} than do alternate methods. See MEASUREMENTS section "Thermal Resistance" for more information.

Electrical Specifications, $T_A = 25^{\circ}\text{C}$

Symbol	Parameters and Test Conditions ^[1]	Units	Min.	Typ.	Max.
$ S_{21E} ^2$	Insertion Power Gain; $V_{CE} = 8 \text{ V}$, $I_C = 35 \text{ mA}$ $f = 2.0 \text{ GHz}$ $f = 4.0 \text{ GHz}$	dB	10.5	11.5 5.5	
$P_{1 \text{ dB}}$	Power Output @ 1 dB Gain Compression $V_{CE} = 8 \text{ V}$, $I_C = 35 \text{ mA}$ $f = 2.0 \text{ GHz}$ $f = 4.0 \text{ GHz}$	dBm		21.0 20.5	
$G_{1 \text{ dB}}$	1 dB Compressed Gain; $V_{CE} = 8 \text{ V}$, $I_C = 35 \text{ mA}$ $f = 2.0 \text{ GHz}$ $f = 4.0 \text{ GHz}$	dB		15.0 10.0	
NF_O	Optimum Noise Figure; $V_{CE} = 8 \text{ V}$, $I_C = 10 \text{ mA}$ $f = 2.0 \text{ GHz}$ $f = 4.0 \text{ GHz}$	dB		1.9 3.0	
G_A	Gain @ NF_O ; $V_{CE} = 8 \text{ V}$, $I_C = 10 \text{ mA}$ $f = 2.0 \text{ GHz}$ $f = 4.0 \text{ GHz}$	dB		14.0 10.5	
f_T	Gain Bandwidth Product; $V_{CE} = 8 \text{ V}$, $I_C = 35 \text{ mA}$	GHz		8.0	
h_{FE}	Forward Current Transfer Ratio; $V_{CE} = 8 \text{ V}$, $I_C = 35 \text{ mA}$	—	30	150	270
I_{CBO}	Collector Cutoff Current; $V_{CB} = 8 \text{ V}$	μA			0.2
I_{EBO}	Emitter Cutoff Current; $V_{EB} = 1 \text{ V}$	μA			2.0
C_{CB}	Collector Base Capacitance ^[1] ; $V_{CB} = 8 \text{ V}$, $f = 1 \text{ MHz}$	pF		0.28	

Note:

1. For this test, the emitter is grounded.

AT-42070 Typical Performance, $T_A = 25^\circ\text{C}$




Figure 1. Insertion Power Gain vs. Collector Current and Frequency.
 $V_{CE} = 8\text{ V}$.




Figure 2. Output Power and 1 dB Compressed Gain vs. Collector Current and Frequency.
 $V_{CE} = 8\text{ V}$.




Figure 3. Output Power and 1 dB Compressed Gain vs. Collector Current and Voltage.
 $f = 2.0\text{ GHz}$.




Figure 4. Insertion Power Gain, Maximum Available Gain and Maximum Stable Gain vs. Frequency.
 $V_{CE} = 8\text{ V}$, $I_C = 35\text{ mA}$.




Figure 5. Noise Figure and Associated Gain vs. Frequency.
 $V_{CE} = 8\text{ V}$, $I_C = 10\text{ mA}$.

AT-42070 Typical Scattering Parameters,

Common Emitter, $Z_O = 50\ \Omega$, $T_A = 25^\circ\text{C}$, $V_{CE} = 8\ \text{V}$, $I_C = 10\ \text{mA}$

Freq. GHz	S_{11}		dB	S_{21}		dB	S_{12}		S_{22}	
	Mag.	Ang.		Mag.	Ang.		Mag.	Ang.	Mag.	Ang.
0.1	.70	-49	28.5	26.56	154	-36.0	.016	77	.91	-18
0.5	.69	-137	21.5	11.85	105	-29.6	.033	34	.50	-41
1.0	.69	-165	16.0	6.34	85	-27.2	.044	29	.40	-44
1.5	.68	-179	12.7	4.33	72	-27.4	.043	37	.38	-48
2.0	.69	169	10.3	3.26	62	-25.6	.052	42	.37	-54
2.5	.69	164	8.5	2.64	56	-25.4	.054	46	.37	-55
3.0	.70	157	6.9	2.22	48	-23.8	.065	52	.39	-63
3.5	.70	151	5.6	1.91	39	-22.4	.076	51	.41	-71
4.0	.69	144	4.5	1.68	30	-21.4	.085	55	.43	-77
4.5	.68	137	3.5	1.50	22	-20.4	.096	49	.46	-83
5.0	.68	128	2.7	1.37	14	-19.4	.107	50	.48	-87
5.5	.68	117	2.0	1.26	5	-18.3	.121	45	.48	-91
6.0	.70	107	1.2	1.15	-3	-17.6	.132	44	.48	-98

AT-42070 Typical Scattering Parameters,

Common Emitter, $Z_O = 50\ \Omega$, $T_A = 25^\circ\text{C}$, $V_{CE} = 8\ \text{V}$, $I_C = 35\ \text{mA}$


Freq. GHz	S_{11}		dB	S_{21}		dB	S_{12}		S_{22}	
	Mag.	Ang.		Mag.	Ang.		Mag.	Ang.	Mag.	Ang.
0.1	.52	-95	33.4	46.52	139	-40.0	.010	50	.77	-29
0.5	.66	-163	23.1	14.33	95	-34.4	.019	46	.34	-42
1.0	.67	179	17.3	7.36	80	-29.6	.033	51	.28	-41
1.5	.67	169	13.9	4.97	69	-28.0	.040	59	.27	-44
2.0	.68	160	11.4	3.74	60	-27.3	.053	59	.27	-51
2.5	.69	157	9.6	3.04	55	-23.8	.065	65	.28	-53
3.0	.69	151	8.1	2.55	47	-22.8	.072	65	.28	-62
3.5	.69	145	6.8	2.20	39	-21.4	.086	59	.30	-72
4.0	.68	139	5.7	1.93	20	-20.2	.097	60	.33	-80
4.5	.67	132	4.7	1.74	22	-19.3	.109	54	.36	-85
5.0	.67	123	4.0	1.59	13	-18.0	.126	50	.38	-90
5.5	.67	113	3.2	1.46	5	-17.2	.138	46	.39	-94
6.0	.69	103	2.5	1.34	-4	-16.4	.152	40	.38	-102

A model for this device is available in the DEVICE MODELS section.

AT-42070 Noise Parameters: $V_{CE} = 8\ \text{V}$, $I_C = 10\ \text{mA}$

Freq. GHz	NF_O dB	Γ_{opt}		$R_N/50$
		Mag	Ang	
0.1	1.0	.05	15	0.13
0.5	1.1	.06	75	0.13
1.0	1.5	.10	126	0.12
2.0	1.9	.23	172	0.11
4.0	3.0	.45	-145	0.17

70 mil Package Dimensions





www.hp.com/go/rf

For technical assistance or the location of
your nearest Hewlett-Packard sales
office, distributor or representative call:

Americas/Canada: 1-800-235-0312 or
408-654-8675

Far East/Australasia: Call your local HP
sales office.

Japan: (81 3) 3335-8152

Europe: Call your local HP sales office.

Data subject to change.
Copyright © 1997 Hewlett-Packard Co.

Obsoletes 5965-8912E
Printed in U.S.A. 5966-4945E (5/98)

SUNSTAR 商斯达实业集团是集研发、生产、工程、销售、代理经销、技术咨询、信息服务等为一体的高科技企业，是专业高科技电子产品生产厂家，是具有 10 多年历史的专业电子元器件供应商，是中国最早和最大的仓储式连锁规模经营大型综合电子零部件代理分销商之一，是一家专业代理和分销世界各大品牌 IC 芯片和电子元器件的连锁经营综合性国际公司，专业经营进口、国产名厂名牌电子元件，型号、种类齐全。在香港、北京、深圳、上海、西安、成都等全国主要电子市场设有直属分公司和产品展示展销窗口门市部专卖店及代理分销商，已在全国范围内建成强大统一的供货和代理分销网络。我们专业代理经销、开发生产电子元器件、集成电路、传感器、微波光电元器件、工控机/DOC/DOM 电子盘、专用电路、单片机开发、MCU/DSP/ARM/FPGA 软件硬件、二极管、三极管、模块等，是您可靠的一站式现货配套供应商、方案提供商、部件功能模块开发配套商。商斯达实业公司拥有庞大的资料库，有数位毕业于著名高校——有中国电子工业摇篮之称的西安电子科技大学（西军电）并长期从事国防尖端科技研究的高级工程师为您精挑细选、量身订做各种高科技电子元器件，并解决各种技术问题。

微波光电部专业代理经销高频、微波、光纤、光电元器件、组件、部件、模块、整机；电磁兼容元器件、材料、设备；微波 CAD、EDA 软件、开发测试仿真工具；微波、光纤仪器仪表。欢迎国外高科技微波、光纤厂商将优秀产品介绍到中国、共同开拓市场。长期大量现货专业批发高频、微波、卫星、光纤、电视、CATV 器件：晶振、VCO、连接器、PIN 开关、变容二极管、开关二极管、低噪晶体管、功率电阻及电容、放大器、功率管、MMIC、混频器、耦合器、功分器、振荡器、合成器、衰减器、滤波器、隔离器、环行器、移相器、调制解调器；光电子元件和组件：红外发射管、红外接收管、光电开关、光敏管、发光二极管和发光二极管组件、半导体激光二极管和激光器组件、光电探测器和光接收组件、光发射接收模块、光纤激光器和光放大器、光调制器、光开关、DWDM 用光发射和接收器件、用户接入系统光收发器件与模块、光纤连接器、光纤跳线/尾纤、光衰减器、光纤适配器、光隔离器、光耦合器、光环行器、光复用器/转换器；无线收发芯片和模组、蓝牙芯片和模组。

更多产品请看本公司产品专用销售网站：

商斯达中国传感器科技信息网：<http://www.sensor-ic.com/>

商斯达工控安防网：<http://www.pc-ps.net/>

商斯达电子元器件网：<http://www.sunstare.com/>

商斯达微波光电产品网：[HTTP://www.rfoe.net/](http://www.rfoe.net/)

商斯达消费电子产品网：<http://www.icasic.com/>

商斯达实业科技产品网：<http://www.sunstars.cn/> 微波元器件销售热线：

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-82884100 83397033 83396822 83398585

传真：0755-83376182 (0) 13823648918 MSN: SUNS8888@hotmail.com

邮编：518033 E-mail: szss20@163.com QQ: 195847376

深圳赛格展销部：深圳华强北路赛格电子市场 2583 号 电话：0755-83665529 25059422

技术支持：0755-83394033 13501568376

欢迎索取免费详细资料、设计指南和光盘；产品凡多，未能尽录，欢迎来电查询。

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL: 010-81159046 82615020 13501189838 FAX: 010-62543996

上海分公司：上海市北京东路 668 号上海赛格电子市场 D125 号

TEL: 021-28311762 56703037 13701955389 FAX: 021-56703037

西安分公司：西安高新开发区 20 所(中国电子科技集团导航技术研究所)

西安劳动南路 88 号电子商城二楼 D23 号

TEL: 029-81022619 13072977981 FAX: 029-88789382