




Product Description

Sirenza Microdevices' SGA-8343 is a high performance Silicon Germanium Heterostructure Bipolar Transistor (SiGe HBT) designed for operation from DC to 6 GHz. The SGA-8343 is optimized for 3V operation but can be biased at 2V for low-voltage battery operated systems. The device provides high gain, low NF, and excellent linearity at a low cost. It can be operated at very low bias currents in applications where high linearity is not required.

The matte tin finish on Sirenza's lead-free package utilizes a post annealing process to mitigate tin whisker formation and is RoHS compliant per EU Directive 2002/95. This package is also manufactured with green molding compounds that contain no antimony trioxide nor halogenated fire retardants.

Typical Performance - 3V, 10mA



SGA-8343

SGA-8343Z

Pb RoHS Compliant & Green Package

Low Noise, High Gain SiGe HBT



Product Features

- Now Available in Lead Free, RoHS Compliant, & Green Packaging
- DC-6 GHz Operation
- 0.9 dB NF_{MIN} @ 0.9 GHz
- 24 dB Gmax @ 0.9 GHz
- |G_{OPT}|=0.10 @ 0.9 GHz
- OIP3 = +28 dBm, P1dB = +9 dBm
- Low Cost, High Performance, Versatility

Applications

- Analog and Digital Wireless Systems
- 3G, Cellular, PCS, RFID
- Fixed Wireless, Pager Systems
- Driver Stage for Low Power Applications
- Oscillators

Symbol	Device Characteristics	Test Conditions $V_{CE}=3V$, $I_{CO}=10mA$, $25^\circ C$ (unless otherwise noted)	Test Frequency	Units	Min.	Typ.	Max.
G_{MAX}	Maximum Available Gain	$Z_S=Z_S^*$, $Z_L=Z_L^*$	0.9 GHz 1.9 GHz 2.4 GHz	dB		23.9 19.3 17.7	
NF	Minimum Noise Figure	$Z_S=\Gamma_{OPT}$, $Z_L=Z_L^*$	0.9 GHz 1.9 GHz 2.4 GHz	dB		0.94 1.10 1.18	
S_{21}	Insertion Gain ^[1]	$Z_S=Z_L=50$ Ohms	0.9 GHz	dB	21.0	22.0	23.0
NF	Noise Figure ^[2]	LNA Application Circuit Board	1.9 GHz	dB		1.40	1.75
Gain	Gain ^[2]	LNA Application Circuit Board	1.9 GHz	dB	15.5	16.5	17.5
OIP ₃	Output Third Order Intercept Point ^[2]	LNA Application Circuit Board	1.9 GHz	dBm	25.8	27.8	
P _{1dB}	Output 1dB Compression Point ^[2]	LNA Application Circuit Board	1.9 GHz	dBm	7.5	9.0	
h_{FE}	DC Current Gain				120	180	300
BV _{CEO}	Collector-Emitter Breakdown Voltage			V	5.7	6.0	
R _{th}	Thermal Resistance	junction-to-lead		°C/W		200	
V _{CE}	Operating Voltage	collector-emitter		V			4.0
I _{CE}	Operating Current	collector-emitter		mA			50

[1] 100% tested - Insertion gain tested using a 50 ohm contact board (no matching circuitry) during final production test.

[2] Sample tested - Samples pulled from each wafer/package lot. Sample test specifications are based on statistical data from sample test measurements. The test fixture is an engineering application circuit board (parts are pressed down on the circuit board). The application circuit represents a trade-off between the optimal noise match and input return loss.

The information provided herein is believed to be reliable at press time. Sirenza Microdevices assumes no responsibility for inaccuracies or omissions. Sirenza Microdevices assumes no responsibility for the use of this information, and all such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Sirenza Microdevices does not authorize or warrant any Sirenza Microdevices product for use in life-support devices and/or systems.

Copyright 2003 Sirenza Microdevices, Inc. All worldwide rights reserved.

303 Technology Court, Broomfield, CO 80021

Phone: (800) SMI-MMIC

<http://www.sirenza.com>



Junction Temperature Calculation

MTTF is inversely proportional to the device junction temperature. For junction temperature and MTTF considerations the device operating conditions should also satisfy the following expression:

$$P_{DC} < (T_J - T_L) / R_{TH}$$

where:

$$P_{DC} = I_{CE} * V_{CE}$$

T_J = Junction Temperature (C)

T_L = Lead Temperature (pin 2) (C)

R_{TH} = Thermal Resistance (C/W)

Biassing Details

The SGA-8343 should be biassed through a dropping resistor or with active bias circuitry to prevent thermal runaway and combat Beta variation. For passive biassing it is recommended that the voltage drop be at least 20% of V_{CE} . A voltage divider from collector-to-base is preferred over a simple series resistor. The effect of Beta variation can be minimized by bleeding $\sim 10^* I_B$ through the shunt resistor.

Absolute Maximum Ratings

Parameter	Symbol	Value	Unit
Collector Current	I_{CE}	72	mA
Base Current	I_B	1	mA
Collector - Emitter Voltage	V_{CE}	5	V
Collector - Base Voltage	V_{CB}	12	V
Emitter - Base Voltage	V_{EB}	4.5	V
RF Input Power	P_{IN}	5	dBm
Storage Temperature Range	T_{stor}	-40 to +150	C
Power Dissipation	P_{DISS}	350	mW
Operating Junction Temperature	T_J	+150	C

Operation of this device beyond any one of these limits may cause permanent damage. For reliable continuous operation, the device voltage and current must not exceed the maximum operating values specified in the table on page 1.

Typical Performance - Engineering Application Circuits (See App Note AN-044)

Freq (GHz)	V _s (V)	V _{CE} (V)	I _{CO} (mA)	NF (dB)	Gain (dB)	P1dB (dBm)	OIP3 ^[3] (dBm)	S11 (dB)	S22 (dB)	Comments
0.90	5.0	3.0	12	1.25	18.2	9	27.3	-16	-18	series feedback
1.575	3.3	2.7	10	1.25	15.7	6.8	26.5	-10	-25	see AN-061
1.90	5.0	3.0	12	1.4	16.5	9	27.8	-9	-24	
2.40	3.3	2.7	10	1.6	14.4	9	27.5	-13	-24	

^[3] P_{OUT}=0 dBm per tone, 1MHz tone spacing

Refer to the application note for additional RF data, PCB layouts, BOMs, biasing instructions, and other key issues to be considered. For the latest application note please visit our site at www.sirenza.com.

Peak RF Performance Under Optimum Matching Conditions

Freq (GHz)	V _{CE} (V)	I _{CO} (mA)	NF _{MIN} ^[4] (dB)	Gmax (dB)	P1dB ^[5] (dBm)	OIP3 ^[6] (dBm)	Z _{SOPT}	Z _{LOPT}
0.90	2	10	0.90	23.7	10	25	Z _{SOPT}	Z _{LOPT}
	3	10	0.94	23.9	13	29		
1.90	2	10	1.05	19.1	10	25	Z _{SOPT}	Z _{LOPT}
	3	10	1.10	19.3	13	29		
2.40	2	10	1.15	17.4	10	25	Z _{SOPT}	Z _{LOPT}
	3	10	1.18	17.7	13	29		


^[4] $Z_S = \Gamma_{OPT}$, $Z_L = Z^*$, The input matching circuit losses have been de-embedded.

^[5] $Z_S = Z_{SOPT}$, $Z_L = Z_{LOPT}$, where Z_{SOPT} and Z_{LOPT} have been tuned for max P1dB (current allowed to drive-up with constant V_{CE})

^[6] $Z_S = Z_{SOPT}$, $Z_L = Z_{LOPT}$, where Z_{SOPT} and Z_{LOPT} have been tuned for max OIP3

Note: Optimum NF, P1dB, and OIP3 performance cannot be achieved simultaneously.

Typical Performance - De-embedded S-Parameters



Note: S-parameters are de-embedded to the device leads with $Z_s = Z_L = 50\Omega$. The device was mounted on a 0.010" PCB with plated-thru holes close to pins 2 and 4. De-embedded s-parameters can be downloaded from our website (www.sirenza.com).

Typical Performance - Noise Parameters - 3V,10mA

Frequency (GHz)	NF _{MIN} ^[7] (dB)	Γ_{OPT} Mag \angle Ang	r _n (Ω)	G _{max} (dB)
0.9	0.94	0.10 \angle 55	0.11	23.88
1.9	1.1	0.17 \angle 125	0.10	19.33
2.4	1.18	0.23 \angle 157	0.09	17.66
3	1.27	0.23 \angle 179	0.09	15.01
4	1.5	0.29 \angle -150	0.12	11.94
5	1.73	0.42 \angle -122	0.18	9.84
6	2.02	0.55 \angle -110	0.24	8.62


^[7] $Z_s = \Gamma_{OPT} Z_L^*$, NF_{MIN} is a noise parameter for which the input matching circuit losses have been de-embedded. The noise parameters were measured using a Maury Microwave Automated Tuner System. The device was mounted on a 0.010" PCB with plated-thru holes close to pins 2 and 4.

**SGA-8343 Low Noise SiGe HBT****Caution: ESD sensitive**

Appropriate precautions in handling, packaging and testing devices must be observed.

Pin Description


Pin #	Function	Description
1	Base	RF Input / Base Bias
2	Emitter	Connection to ground. Use multiple via holes to reduce emitter inductance.
3	Collector	RF Output / Collector Bias
4	Emitter	Same as Pin 2

MARKING**Part Number Ordering Information**


Part Number	Reel Size	Devices/Reel
SGA-8343	7"	3000
SGA-8343Z	7"	3000

Part Symbolization

The part will be symbolized with the "A83" or "A83Z" designator and a dot signifying pin 1 on the top surface of the package.

Recommended PCB Layout

Use multiple plated-through vias located close to the package pins to ensure a good RF ground connection to a continuous groundplane on the backside of the board.

Package Dimensions

NOTE:

1. ALL DIMENSIONS ARE IN MILLIMETERS.
2. DIMENSIONS ARE INCLUSIVE OF PLATING.
3. DIMENSIONS ARE EXCLUSIVE OF MOLD FLASH & METAL FORM.
4. ALL SPECIFICATIONS COMPLY TO EIAJ SC70.
5. DIE IS FACING UP FOR MOLD AND FACING DOWN FOR TRIM/FORM. i.e.:REVERSE TRIM/FORM.
6. PACKAGE SURFACE TO BE MIRROR FINISH.

SYMBOL	MIN	MAX
E	1.15	1.35
D	1.85	2.25
HE	1.80	2.40
A	0.80	1.10
A2	0.80	1.00
A1	0.00	0.10
Q1	0.10	0.40
e	0.65 BSC	
b	0.25	0.40
b1	0.55	0.70
c	0.10	0.18
L	0.10	0.30

SUNSTAR 商斯达实业集团是集研发、生产、工程、销售、代理经销、技术咨询、信息服务等为一体的高科技企业，是专业高科技电子产品生产厂家，是具有 10 多年历史的专业电子元器件供应商，是中国最早和最大的仓储式连锁规模经营大型综合电子零部件代理分销商之一，是一家专业代理和分销世界各大品牌 IC 芯片和电子元器件的连锁经营综合性国际公司，专业经营进口、国产名厂名牌电子元件，型号、种类齐全。在香港、北京、深圳、上海、西安、成都等全国主要电子市场设有直属分公司和产品展示展销窗口门市部专卖店及代理分销商，已在全国范围内建成强大统一的供货和代理分销网络。我们专业代理经销、开发生产电子元器件、集成电路、传感器、微波光电元器件、工控机/DOC/DOM 电子盘、专用电路、单片机开发、MCU/DSP/ARM/FPGA 软件硬件、二极管、三极管、模块等，是您可靠的一站式现货配套供应商、方案提供商、部件功能模块开发配套商。商斯达实业公司拥有庞大的资料库，有数位毕业于著名高校——有中国电子工业摇篮之称的西安电子科技大学（西军电）并长期从事国防尖端科技研究的高级工程师为您精挑细选、量身订做各种高科技电子元器件，并解决各种技术问题。

微波光电部专业代理经销高频、微波、光纤、光电元器件、组件、部件、模块、整机；电磁兼容元器件、材料、设备；微波 CAD、EDA 软件、开发测试仿真工具；微波、光纤仪器仪表。欢迎国外高科技微波、光纤厂商将优秀产品介绍到中国、共同开拓市场。长期大量现货专业批发高频、微波、卫星、光纤、电视、CATV 器件：晶振、VCO、连接器、PIN 开关、变容二极管、开关二极管、低噪晶体管、功率电阻及电容、放大器、功率管、MMIC、混频器、耦合器、功分器、振荡器、合成器、衰减器、滤波器、隔离器、环行器、移相器、调制解调器；光电子元器件和组件：红外发射管、红外接收管、光电开关、光敏管、发光二极管和发光二极管组件、半导体激光二极管和激光器组件、光电探测器和光接收组件、光发射接收模块、光纤激光器和光放大器、光调制器、光开关、DWDM 用光发射和接收器件、用户接入系统光光收发器件与模块、光纤连接器、光纤跳线/尾纤、光衰减器、光纤适配器、光隔离器、光耦合器、光环行器、光复用器/转换器；无线收发芯片和模组、蓝牙芯片和模组。

更多产品请看本公司产品专用销售网站：

商斯达中国传感器科技信息网：<http://www.sensor-ic.com/>

商斯达工控安防网：<http://www.pc-ps.net/>

商斯达电子元器件网：<http://www.sunstare.com/>

商斯达微波光电产品网：<HTTP://www.rfoe.net/>

商斯达消费电子产品网：<http://www.icasic.com/>

商斯达实业科技产品网：<http://www.sunstars.cn/> 微波元器件销售热线：

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-82884100 83397033 83396822 83398585

传真：0755-83376182 (0) 13823648918 MSN：SUNS8888@hotmail.com

邮编：518033 E-mail：szss20@163.com QQ：195847376

深圳赛格展销部：深圳华强北路赛格电子市场 2583 号 电话：0755-83665529 25059422

技术支持：0755-83394033 13501568376

欢迎索取免费详细资料、设计指南和光盘；产品凡多，未能尽录，欢迎来电查询。

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL：010-81159046 82615020 13501189838 FAX：010-62543996

上海分公司：上海市北京东路 668 号上海赛格电子市场 D125 号

TEL：021-28311762 56703037 13701955389 FAX：021-56703037

西安分公司：西安高新区 20 所(中国电子科技集团导航技术研究所)

西安劳动南路 88 号电子商城二楼 D23 号

TEL：029-81022619 13072977981 FAX:029-88789382