

## 3ch VIDEO AMPLIFIER FOR COLOR DIFFERENCE SIGNAL


### ■GENERAL DESCRIPTION

The NJM2569 is a 3ch video amplifier for color difference signal (R-Y,B-Y).

It composes the output circuit of video items for color difference signal, because prepares clamp circuit, LPF, GCA.

Also it is suitable for portable items because of power save circuit.

### ■OUTLINE PACKAGE




NJM2569V

### ■FEATURES

- Operating Voltage 4.5 to 5.5V
- Operating Current 17.0mA typ. at Vcc1=4.8V  
7.0mA typ. at Vcc2=4.8V
- Operating Current at Power Save 1.5mA typ. at Vcc1=4.8V  
5.0uA typ. at Vcc2=4.8V
- Internal Low Pass Filter
- Internal Gain Control Amplifier
- Bipolar Technology
- Package Outline SSOP20

### ■BLOCK DIAGRAM



### PIN FUNCTION

- 1.Vcc1
- 2.Cb in
- 3.GCA CTL2
- 4.Cr in
- 5.GCA CTL3
- 6.CLAMP3
- 7.Cr out
- 8.GND1
- 9.Cb out
- 10.GND2(Driver)
- 11.Y<sub>SAG</sub>
- 12.Yout
- 13.Vcc2(Driver)
- 14.Vref
- 15.CLAMP2
- 16.NC
- 17.CLAMP1
- 18.GCA CTL1
- 19.CP
- 20.Yin

# NJM2569

## ■ABSOLUTE MAXIMUM RATINGS

(Ta=25°C)

| PARAMETER                   | SYMBOL         | RATINGS     | UNIT |
|-----------------------------|----------------|-------------|------|
| Supply Voltage              | Vcc            | 7.0         | V    |
| Power Dissipation           | P <sub>D</sub> | 300         | mW   |
| Operating Temperature Range | Topr           | -40 to +85  | °C   |
| Storage Temperature Range   | Tstg           | -40 to +125 | °C   |

## ■RECOMMENDED OPERATING CONDITIONS

(Ta=25°C)

| PARAMETER         | SYMBOL | TEST CONDITION      | MIN. | TYP. | MAX. | UNIT |
|-------------------|--------|---------------------|------|------|------|------|
| Operating Voltage | Vopr   | Vcc1,Vcc2-GND1,GND2 | 4.5  | 4.8  | 5.5  | V    |

## ■ELECTRICAL CHARACTERISTICS (Vcc1=4.8V,Vcc2=4.8V,RL=75Ω,Ta=25°C)

| PARAMETER                         | SYMBOL | TEST CONDITION       | MIN. | TYP. | MAX.  | UNIT |
|-----------------------------------|--------|----------------------|------|------|-------|------|
| Operating Current 1               | Icc1   | Vcc1                 | -    | 17.0 | 27.0  | mA   |
| Operating Current 2               | Icc2   | Vcc2                 | -    | 7.0  | 12.0  | mA   |
| Operating Current at Power Save 1 | Icc1ps | Vcc1, At Power Save  | -    | 1.5  | 5.0   | mA   |
| Operating Current at Power Save 2 | Icc2ps | Vcc2, At Power Ssave | -    | 5.0  | 100.0 | uA   |

### [ Y Amplifier Characteristics ]

|                |                  |  |      |      |      |    |
|----------------|------------------|--|------|------|------|----|
| Voltage Gain 1 | G <sub>VY1</sub> | Y <sub>IN</sub> →Y <sub>OUT</sub> , GCACTL1=0.5V, 0.5Vpp, Input Sine Wave Video Signal (100kHz, 0.35Vpp Sine Wave) | -2.6 | 0.4  | 3.4  | dB |
| Voltage Gain 2 | G <sub>VY2</sub> | Y <sub>IN</sub> →Y <sub>OUT</sub> , GCACTL1=1.3V, 0.5Vpp, Input Sine Wave Video Signal (100kHz, 0.35Vpp Sine Wave) | 3.3  | 6.3  | 9.3  | dB |
| Voltage Gain 3 | G <sub>VY3</sub> | Y <sub>IN</sub> →Y <sub>OUT</sub> , GCACTL1=2.5V, 0.5Vpp, Input Sine Wave Video Signal (100kHz, 0.35Vpp Sine Wave) | 8.2  | 11.2 | 14.2 | dB |

### [ Cb Amplifier Characteristics ]

|                |                   |   |      |      |      |    |
|----------------|-------------------|---|------|------|------|----|
| Voltage Gain 1 | G <sub>VCb1</sub> | Cb <sub>IN</sub> →Cb <sub>OUT</sub> , GCACTL2=0.5V, 0.35Vpp, Input Sine Wave Video Signal (100kHz, 0.35Vpp Sine Wave) | -2.6 | 0.4  | 3.4  | dB |
| Voltage Gain 2 | G <sub>VCb2</sub> | Cb <sub>IN</sub> →Cb <sub>OUT</sub> , GCACTL2=1.3V, 0.35Vpp, Input Sine Wave Video Signal (100kHz, 0.35Vpp Sine Wave) | 3.3  | 6.3  | 9.3  | dB |
| Voltage Gain 3 | G <sub>VCb3</sub> | Cb <sub>IN</sub> →Cb <sub>OUT</sub> , GCACTL2=2.5V, 0.35Vpp, Input Sine Wave Video Signal (100kHz, 0.35Vpp Sine Wave) | 8.2  | 11.2 | 14.2 | dB |

### [ Cr Amplifier Characteristics ]

|                |                   |   |      |      |      |    |
|----------------|-------------------|---|------|------|------|----|
| Voltage Gain 1 | G <sub>VCr1</sub> | Cr <sub>IN</sub> →Cr <sub>OUT</sub> , GCACTL3=0.5V, 0.35Vpp, Input Sine Wave Video Signal (100kHz, 0.35Vpp Sine Wave) | -2.6 | 0.4  | 3.4  | dB |
| Voltage Gain 2 | G <sub>VCr2</sub> | Cr <sub>IN</sub> →Cr <sub>OUT</sub> , GCACTL3=1.3V, 0.35Vpp, Input Sine Wave Video Signal (100kHz, 0.35Vpp Sine Wave) | 3.3  | 6.3  | 9.3  | dB |
| Voltage Gain 3 | G <sub>VCr3</sub> | Cr <sub>IN</sub> →Cr <sub>OUT</sub> , GCACTL3=2.5V, 0.35Vpp, Input Sine Wave Video Signal (100kHz, 0.35Vpp Sine Wave) | 8.2  | 11.2 | 14.2 | dB |

### [ GCA Control Signal ]

|        |                 |   |     |   |     |   |
|--------|-----------------|---|-----|---|-----|---|
| GCACTL | V <sub>GH</sub> | GCACTL1,2,3 Input control voltage range | 0.5 | - | Vcc | V |
|        | V <sub>GL</sub> | MUTE change value                       | 0   | - | 0.3 |   |

Ver.1


## ■ELECTRICAL CHARACTERISTICS (Vcc1=4.8V,Vcc2=4.8V,RL=75Ω,Ta=25°C)

| PARAMETER                                 | SYMBOL                | TEST CONDITION  | MIN. | TYP.  | MAX.  | UNIT |
|---|-----------------------|---|------|-------|-------|------|
| [ Filter Characteristics ]                |                       |   |      |       |       |      |
| LPF(Y <sub>IN</sub> →Y <sub>OUT</sub> )   | Gf <sub>Y6.75M</sub>  | 6.75MHz/100kHz, input sine wave video signal (100mVpp sine wave)  | -3.0 | -1.0  | -     | dB   |
|   | Gf <sub>Y12M</sub>    | 12MHz/100kHz, input sine wave video signal (100mVpp sine wave)  | -    | -3.0  | -     | dB   |
|   | Gf <sub>Y27M</sub>    | 27MHz/100kHz, input sine wave video signal (100mVpp sine wave)  | -    | -40.0 | -15.0 | dB   |
| LPF(Cb <sub>IN</sub> →Cb <sub>OUT</sub> ) | Gf <sub>Cb6.75M</sub> | 6.75MHz/100kHz, input sine wave video signal (100mVpp sine wave)  | -3.0 | -1.0  | -     | dB   |
|   | Gf <sub>Cb27M</sub>   | 27MHz/100kHz, input sine wave video signal (100mVpp sine wave)  | -    | -40.0 | -15.0 | dB   |
| LPF(Cr <sub>IN</sub> →Cr <sub>OUT</sub> ) | Gf <sub>Cr6.75M</sub> | 6.75MHz/100kHz, input sine wave video signal (100mVpp sine wave)  | -3.0 | -1.0  | -     | dB   |
|   | Gf <sub>Cr27M</sub>   | 27MHz/100kHz, input sine wave video signal (100mVpp sine wave)  | -    | -40.0 | -15.0 | dB   |
| [ Crosstalk Characteristics ]             |                       |   |      |       |       |      |
| Crosstalk 1                               | CT1                   | Input Red Field Signal(3.58MHz) to Y <sub>IN</sub> . Measure Cr <sub>OUT</sub> /Y <sub>OUT</sub> .                    | -    | -50   | -     | dB   |
| Crosstalk 2                               | CT2                   | Input Red Field Signal(3.58MHz) to Y <sub>IN</sub> . Measure Cb <sub>OUT</sub> /Y <sub>OUT</sub> .                    | -    | -50   | -     | dB   |
| Crosstalk 3                               | CT3                   | Input Red Field Signal(3.58MHz) to Cb <sub>IN</sub> . Measure Y <sub>OUT</sub> /Cb <sub>OUT</sub> .                   | -    | -50   | -     | dB   |
| Crosstalk 4                               | CT4                   | Input Red Field Signal(3.58MHz) to Cb <sub>IN</sub> . Measure Cr <sub>OUT</sub> /Cb <sub>OUT</sub> .                  | -    | -50   | -     | dB   |
| Crosstalk 5                               | CT5                   | Input Red Field Signal(3.58MHz) to Cr <sub>IN</sub> . Measure Y <sub>OUT</sub> /Cr <sub>OUT</sub> .                   | -    | -50   | -     | dB   |
| Crosstalk 6                               | CT6                   | Input Red Field Signal(3.58MHz) to Cr <sub>IN</sub> . Measure Cb <sub>OUT</sub> /Cr <sub>OUT</sub> .                  | -    | -50   | -     | dB   |
| MUTE Crosstalk 1                          | MCT1                  | Input Red Field Signal(3.58MHz) to Y <sub>IN</sub> . Measure ratio of Y <sub>IN</sub> to Y <sub>OUT</sub> at MUTE.    | -    | -50   | -     | dB   |
| MUTE Crosstalk 2                          | MCT2                  | Input Red Field Signal(3.58MHz) to Cb <sub>IN</sub> . Measure ratio of Cb <sub>IN</sub> to Cb <sub>OUT</sub> at MUTE. | -    | -50   | -     | dB   |
| MUTE Crosstalk 3                          | MCT3                  | Input Red Field Signal(3.58MHz) to Cr <sub>IN</sub> . Measure ratio of Cr <sub>IN</sub> to Cr <sub>OUT</sub> at MUTE. | -    | -50   | -     | dB   |
| [ S/N Ratio]                              |                       |   |      |       |       |      |
| Y System S/N                              | SN <sub>Y</sub>       | Band width 100kHz to 6MHz, RL=75Ω, Input 100% White Video Signal. Measure Y <sub>OUT</sub> .                          | -    | -55   | -     | dB   |
| Cb System S/N                             | SN <sub>Cb</sub>      | Band width 100kHz to 6MHz, RL=75Ω, Input 100% White Video Signal. Measure Cb <sub>OUT</sub> .                         | -    | -55   | -     | dB   |
| Cr System S/N                             | SN <sub>Cr</sub>      | Band width 100kHz to 6MHz, RL=75Ω, Input 100% White Video Signal. Measure Cr <sub>OUT</sub> .                         | -    | -55   | -     | dB   |
| [ CP Signal *]                            |                       |   |      |       |       |      |
| CP Input Change Voltage                   | VCP <sub>H</sub>      | ON level  | 2.4  | -     | Vcc   | V    |
|   | VCP <sub>L</sub>      | OFF level   | 0    | -     | 0.8   |      |


# NJM2569

## \*CP Input

Don't put CP signal on Sync signal and picture period. Keep margin of 0.2 $\mu$ S over of  $\Delta t1$  and  $\Delta t2$ .




## TEST CIRCUIT




## ■ TYPICAL CHARACTERISTICS


Operating Current 1 vs. Supply Voltage  
(Ta=25°C)




Operating Current 2 vs. Supply Voltage  
(Ta=25°C)




Operating Current at Power Save 1 vs. Supply Voltage  
(Ta=25°C)




Operating Current at Power Save 2 vs. Supply Voltage  
(Ta=25°C)



Y System Filter Characteristics  
(Vcc=4.8V)




Cb System Filter Characteristics  
(Vcc=4.8V)




## ■ TYPICAL CHARACTERISTICS


Cr System Filter Characteristics  
(Vcc=4.8V)




Y System GAIN vs. GCACTL  
(Vcc=4.8V)



Cb System GAIN vs. GCACTL  
(Vcc=4.8V)



Cr System GAIN vs. GCACTL  
(Vcc=4.8V)



## MEMO

[CAUTION]  
The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.