

# DATA SHEET

**BFG198**  
NPN 8 GHz wideband transistor

Product specification  
File under Discrete Semiconductors, SC14

1995 Sep 12

**NPN 8 GHz wideband transistor****BFG198****DESCRIPTION**

NPN planar epitaxial transistor in a plastic SOT223 envelope, intended for wideband amplifier applications. The device features a high gain and excellent output voltage capabilities.

**PINNING**

PIN	DESCRIPTION
1	emitter
2	base
3	emitter
4	collector




Fig.1 SOT223.

**QUICK REFERENCE DATA**

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
$V_{CBO}$	collector-base voltage	open emitter	—	—	20	V
$V_{CEO}$	collector-emitter voltage	open base	—	—	10	V
$I_C$	DC collector current		—	—	100	mA
$P_{tot}$	total power dissipation	up to $T_s = 135^\circ\text{C}$ (note 1)	—	—	1	W
$h_{FE}$	DC current gain	$I_C = 50 \text{ mA}; V_{CE} = 5 \text{ V}; T_j = 25^\circ\text{C}$	40	90	—	
$f_T$	transition frequency	$I_C = 50 \text{ mA}; V_{CE} = 8 \text{ V}; f = 1 \text{ GHz}; T_{amb} = 25^\circ\text{C}$	—	8	—	GHz
$G_{UM}$	maximum unilateral power gain	$I_C = 50 \text{ mA}; V_{CE} = 8 \text{ V}; f = 500 \text{ MHz}; T_{amb} = 25^\circ\text{C}$	—	18	—	dB
		$I_C = 50 \text{ mA}; V_{CE} = 8 \text{ V}; f = 800 \text{ MHz}; T_{amb} = 25^\circ\text{C}$	—	15	—	dB
$V_o$	output voltage	$d_{im} = -60 \text{ dB}; I_C = 70 \text{ mA}; V_{CE} = 8 \text{ V}; R_L = 75 \Omega; T_{amb} = 25^\circ\text{C}; f_{(p+q-r)} = 793.25 \text{ MHz}$	—	700	—	mV

**LIMITING VALUES**

In accordance with the Absolute Maximum System (IEC 134).

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.	UNIT
$V_{CBO}$	collector-base voltage	open emitter	—	20	V
$V_{CEO}$	collector-emitter voltage	open base	—	10	V
$V_{EBO}$	emitter-base voltage	open collector	—	2.5	V
$I_C$	DC collector current		—	100	mA
$P_{tot}$	total power dissipation	up to $T_s = 135^\circ\text{C}$ (note 1)	—	1	W
$T_{stg}$	storage temperature		-65	+150	°C
$T_j$	junction temperature		—	175	°C

**Note**

1.  $T_s$  is the temperature at the soldering point of the collector tab.

## NPN 8 GHz wideband transistor

BFG198

## THERMAL CHARACTERISTICS

SYMBOL	PARAMETER	CONDITIONS	VALUE	UNIT
$R_{th\ j-s}$	thermal resistance from junction to soldering point	up to $T_s = 135^\circ\text{C}$ (note 1)	40	K/W

**Note**

- $T_s$  is the temperature at the soldering point of the collector tab.

## CHARACTERISTICS

 $T_j = 25^\circ\text{C}$  unless otherwise specified.

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
$I_{CBO}$	collector cut-off current	$I_E = 0; V_{CB} = 5\text{ V}$	–	–	100	nA
$h_{FE}$	DC current gain	$I_C = 50\text{ mA}; V_{CE} = 5\text{ V}$	40	90	–	
$C_c$	collector capacitance	$I_E = i_e = 0; V_{CB} = 8\text{ V}; f = 1\text{ MHz}$	–	1.5	–	pF
$C_e$	emitter capacitance	$I_C = i_c = 0; V_{EB} = 0.5\text{ V}; f = 1\text{ MHz}$	–	4	–	pF
$C_{re}$	feedback capacitance	$I_C = 0; V_{CE} = 8\text{ V}; f = 1\text{ MHz}$	–	0.8	–	pF
$f_T$	transition frequency	$I_C = 50\text{ mA}; V_{CE} = 8\text{ V}; f = 1\text{ GHz}; T_{amb} = 25^\circ\text{C}$	–	8	–	GHz
$G_{UM}$	maximum unilateral power gain; note 1	$I_C = 50\text{ mA}; V_{CE} = 8\text{ V}; f = 500\text{ MHz}; T_{amb} = 25^\circ\text{C}$	–	18	–	dB
		$I_C = 50\text{ mA}; V_{CE} = 8\text{ V}; f = 800\text{ MHz}; T_{amb} = 25^\circ\text{C}$	–	15	–	dB
$V_o$	output voltage	note 2	–	750	–	mV
		note 3	–	700	–	mV
$d_2$	second order intermodulation distortion	note 4	–	–55	–	dB

**Note**

- $G_{UM}$  is the maximum unilateral power gain, assuming  $S_{12}$  is zero and  $G_{UM} = 10 \log \frac{|s_{21}|^2}{(1 - |s_{11}|^2)(1 - |s_{22}|^2)}$  dB.
- $d_{im} = -60\text{ dB}$  (DIN 45004B);  $I_C = 70\text{ mA}; V_{CE} = 8\text{ V}; R_L = 75\Omega; T_{amb} = 25^\circ\text{C}$ ;  
 $V_p = V_o$  at  $d_{im} = -60\text{ dB}$ ;  
 $V_q = V_o - 6\text{ dB}; f_p = 445.25\text{ MHz}$ ;  
 $V_r = V_o - 6\text{ dB}; f_q = 453.25\text{ MHz}; f_r = 455.25\text{ MHz}$   
measured at  $f_{(p+q-r)} = 443.25\text{ MHz}$ .
- $d_{im} = -60\text{ dB}$  (DIN 45004B);  $I_C = 70\text{ mA}; V_{CE} = 8\text{ V}; R_L = 75\Omega; T_{amb} = 25^\circ\text{C}$ ;  
 $V_p = V_o$  at  $d_{im} = -60\text{ dB}; f_p = 795.25\text{ MHz}$ ;  
 $V_q = V_o - 6\text{ dB}; f_q = 803.25\text{ MHz}$ ;  
 $V_r = V_o - 6\text{ dB}; f_r = 805.25\text{ MHz}$ ;  
measured at  $f_{(p+q-r)} = 793.25\text{ MHz}$ .
- $I_C = 50\text{ mA}; V_{CE} = 8\text{ V}; V_o = 50\text{ dBmV}$ ;  
 $f_{(p+q)} = 810\text{ MHz}; f_p = 250\text{ MHz}; f_q = 560\text{ MHz}$ .

## NPN 8 GHz wideband transistor

BFG198




Fig.2 Intermodulation distortion and second order intermodulation distortion test circuit.

## List of components (see test circuit)

DESIGNATION	DESCRIPTION	VALUE	UNIT	DIMENSIONS	CATALOGUE NO.
C2	multilayer ceramic capacitor	1.2	pF		2222 851 12128
C1, C4, C6, C7	multilayer ceramic capacitor	10	nF		2222 590 08627
C3	multilayer ceramic capacitor	10	nF		2222 851 12128
C5 (note 1)	multilayer ceramic capacitor	10	nF		2222 629 08103
C8	multilayer ceramic capacitor	1.5	pF		2222 851 12158
L1 (note 1)	1.5 turns 0.4 mm copper wire			int. dia. 3 mm; winding pitch 1 mm	
L2	microstripline	75	Ω	length 22 mm; width 2.5 mm	
L3 (note 1)	0.4 mm copper wire	≈24	nH	length 30 mm	
L4 (note 1)	0.4 mm copper wire	≈3.6	nH	length 4 mm	
L5	microstripline	75	Ω	length 19 mm; width 2.5 mm	
L6	Ferroxcube choke	5	μH		3122 108 20153
R1	metal film resistor	10	Ω		2322 180 73103
R2 (note 1)	metal film resistor	220	Ω		2322 180 73221
R3, R4	metal film resistor	30	Ω		2322 180 73309

## Note

- Components C5, L1, L3, L4, and R2 are mounted on the underside of the PCB.

The circuit is constructed on a double copper-clad printed circuit board with PTFE dielectric ( $\epsilon_r = 2.2$ ); thickness  $1/16$  inch; thickness of copper sheet  $2 \times 35 \mu\text{m}$ ; see Fig.2.

## NPN 8 GHz wideband transistor

BFG198






Fig.3 Intermodulation distortion and second order intermodulation distortion printed-circuit board.

## NPN 8 GHz wideband transistor

BFG198




Fig.4 Power derating curve.


 $V_{CE} = 5$  V;  $T_j = 25$   $^{\circ}$ C.

Fig.5 DC current gain as a function of collector current.


 $I_E = 0$ ;  $f = 1$  MHz;  $T_j = 25$   $^{\circ}$ C.

Fig.6 Feedback capacitance as a function of collector-base voltage.



 $V_{CE} = 8$  V;  $f = 1$  GHz;  $T_{amb} = 25$   $^{\circ}$ C.

Fig.7 Transition frequency as a function of collector current.


## NPN 8 GHz wideband transistor

BFG198




$I_C = 50 \text{ mA}$ ;  $V_{CE} = 8 \text{ V}$ ;  $T_{amb} = 25^\circ\text{C}$ ;

Fig.8 Maximum gain as a function of frequency.




$V_{CE} = 8 \text{ V}$ ;  $V_o = 750 \text{ mV}$ ;  $T_{amb} = 25^\circ\text{C}$ ;  
 $f_{(p+q-r)} = 443.25 \text{ MHz}$ .

Fig.9 Intermodulation distortion as a function of collector current.



$V_{CE} = 8 \text{ V}$ ;  $V_o = 700 \text{ mV}$ ;  $T_{amb} = 25^\circ\text{C}$ ;  
 $f_{(p+q)} = 793.25 \text{ MHz}$ .

Fig.10 Intermodulation distortion as a function of collector current.




$V_{CE} = 8 \text{ V}$ ;  $V_o = 50 \text{ dBmV}$ ;  $T_{amb} = 25^\circ\text{C}$ ;  
 $f_{(p+q)} = 450 \text{ MHz}$ .

Fig.11 Second order intermodulation distortion as a function of collector current.



## NPN 8 GHz wideband transistor

BFG198




## NPN 8 GHz wideband transistor

BFG198

 $I_C = 50 \text{ mA}; V_{CE} = 8 \text{ V}; T_{amb} = 25^\circ\text{C}; Z_0 = 50 \Omega.$ Fig.13 Common emitter input reflection coefficient ( $S_{11}$ ). $I_C = 50 \text{ mA}; V_{CE} = 8 \text{ V}; T_{amb} = 25^\circ\text{C}.$ Fig.14 Common emitter forward transmission coefficient ( $S_{21}$ ).


## NPN 8 GHz wideband transistor

BFG198



$I_C = 50 \text{ mA}; V_{CE} = 8 \text{ V}; T_{amb} = 25^\circ\text{C}.$

Fig.15 Common emitter reverse transmission coefficient ( $S_{12}$ ).




$I_C = 50 \text{ mA}; V_{CE} = 8 \text{ V}; T_{amb} = 25^\circ\text{C}; Z_0 = 50 \Omega.$

Fig.16 Common emitter output reflection coefficient ( $S_{22}$ ).

## NPN 8 GHz wideband transistor

BFG198

## PACKAGE OUTLINE



Dimensions in mm.

Fig.17 SOT223.

**NPN 8 GHz wideband transistor****BFG198****DEFINITIONS**

<b>Data sheet status</b>	
Objective specification	This data sheet contains target or goal specifications for product development.
Preliminary specification	This data sheet contains preliminary data; supplementary data may be published later.
Product specification	This data sheet contains final product specifications.
Short-form specification	The data in this specification is extracted from a full data sheet with the same type number and title. For detailed information see the relevant data sheet or data handbook.
<b>Limiting values</b>	
Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.	
<b>Application information</b>	
Where application information is given, it is advisory and does not form part of the specification.	

**LIFE SUPPORT APPLICATIONS**

These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips for any damages resulting from such improper use or sale.

SUNSTAR 商斯达实业集团是集研发、生产、工程、销售、代理经销、技术咨询、信息服务等为一体的高科技企业，是专业高科技电子产品生产厂家，是具有 10 多年历史的专业电子元器件供应商，是中国最早和最大的仓储式连锁规模经营大型综合电子零部件代理分销商之一，是一家专业代理和分销世界各大品牌 IC 芯片和电子元器件的连锁经营综合性国际公司，专业经营进口、国产名厂名牌电子元件，型号、种类齐全。在香港、北京、深圳、上海、西安、成都等全国主要电子市场设有直属分公司和产品展示展销窗口门市部专卖店及代理分销商，已在全国范围内建成强大统一的供货和代理分销网络。我们专业代理经销、开发生产电子元器件、集成电路、传感器、微波光电元器件、工控机/DOC/DOM 电子盘、专用电路、单片机开发、MCU/DSP/ARM/FPGA 软件硬件、二极管、三极管、模块等，是您可靠的一站式现货配套供应商、方案提供商、部件功能模块开发配套商。商斯达实业公司拥有庞大的资料库，有数位毕业于著名高校——有中国电子工业摇篮之称的西安电子科技大学（西军电）并长期从事国防尖端科技研究的高级工程师为您精挑细选、量身订做各种高科技电子元器件，并解决各种技术问题。

微波光电部专业代理经销高频、微波、光纤、光电元器件、组件、部件、模块、整机；电磁兼容元器件、材料、设备；微波 CAD、EDA 软件、开发测试仿真工具；微波、光纤仪器仪表。欢迎国外高科技微波、光纤厂商将优秀产品介绍到中国、共同开拓市场。长期大量现货专业批发高频、微波、卫星、光纤、电视、CATV 器件：晶振、VCO、连接器、PIN 开关、变容二极管、开关二极管、低噪晶体管、功率电阻及电容、放大器、功率管、MMIC、混频器、耦合器、功分器、振荡器、合成器、衰减器、滤波器、隔离器、环行器、移相器、调制解调器；光电子元器件和组件：红外发射管、红外接收管、光电开关、光敏管、发光二极管和发光二极管组件、半导体激光二极管和激光器组件、光电探测器和光接收组件、光发射接收模块、光纤激光器和光放大器、光调制器、光开关、DWDM 用光发射和接收器件、用户接入系统光光收发器件与模块、光纤连接器、光纤跳线/尾纤、光衰减器、光纤适配器、光隔离器、光耦合器、光环行器、光复用器/转换器；无线收发芯片和模组、蓝牙芯片和模组。

更多产品请看本公司产品专用销售网站：

商斯达中国传感器科技信息网：<http://www.sensor-ic.com/>

商斯达工控安防网：<http://www.pc-ps.net/>

商斯达电子元器件网：<http://www.sunstare.com/>

商斯达微波光电产品网：<HTTP://www.rfoe.net/>

商斯达消费电子产品网：<http://www.icasic.com/>

商斯达实业科技产品网：<http://www.sunstars.cn/> 微波元器件销售热线：

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-82884100 83397033 83396822 83398585

传真：0755-83376182 (0) 13823648918 MSN：[SUNS8888@hotmail.com](mailto:SUNS8888@hotmail.com)

邮编：518033 E-mail：[szss20@163.com](mailto:szss20@163.com) QQ：195847376

深圳赛格展销部：深圳华强北路赛格电子市场 2583 号 电话：0755-83665529 25059422

技术支持：0755-83394033 13501568376

欢迎索取免费详细资料、设计指南和光盘；产品凡多，未能尽录，欢迎来电查询。

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL：010-81159046 82615020 13501189838 FAX：010-62543996

上海分公司：上海市北京东路 668 号上海赛格电子市场 D125 号

TEL：021-28311762 56703037 13701955389 FAX：021-56703037

西安分公司：西安高新区 20 所(中国电子科技集团导航技术研究所)

西安劳动南路 88 号电子商城二楼 D23 号

TEL：029-81022619 13072977981 FAX:029-88789382