

## Standex 干簧管

| 产品型号  | 管径<br>mm | 管长<br>mm | 触点 | 吸合<br>(AT) | 触点<br>材料 | 触点电<br>阻 m $\Omega$ | 击穿电压<br>V (DC) | 绝缘电<br>阻 $\Omega$ | 静电<br>电容 | 触点额定功率 | 最大开关电压<br>(V) | 最大开关电流<br>(A) |
|-------|----------|----------|----|------------|----------|---------------------|----------------|-------------------|----------|--------|---------------|---------------|
| GR400 | 1.8      | 10       | 1A | 7-30       | Rh       | 200                 | 150            | 10 <sup>12</sup>  | 0.2pF    | 5W     | 50DC/50AC     | 0.5DC&AC      |
| GR501 | 2.3      | 12.7     | 1A | 7-30       | Rh       | 150                 | 200            | 10 <sup>12</sup>  | 0.3pF    | 10W    | 100DC/125AC   | 0.5DC&AC      |
| GR560 | 2.3      | 14.2     | 1A | 10-50      | Rh       | 100                 | 200            | 10 <sup>12</sup>  | 0.2pF    | 10W    | 100DC/125AC   | 1.0DC&AC      |
| GR100 | 2.5      | 20.3     | 1A | 10-60      | Rh       | 100                 | 250            | 10 <sup>12</sup>  | 0.2pF    | 10W    | 100DC/150AC   | 1.0DC&AC      |
| NL126 | 2.5      | 20.3     | 1A | 15-60      | Rh       | 100                 | 250            | 10 <sup>12</sup>  | 0.3pF    | 50W    | 200DC/150AC   | 1.5DC&AC      |
| TS501 | 2.5      | 13.5     | 1A | 10-100     | Rh       | 250                 | 200            | 10 <sup>9</sup>   | 0.2pF    | 5W     | 50DC/75AC     | 0.3DC&AC      |
| TS560 | 2.3      | 14.2     | 1A | 10-100     | Rh       | 250                 | 200            | 10 <sup>9</sup>   | 0.2pF    | 5W     | 100DC/125AC   | 0.5DC&AC      |
| TS100 | 2.8      | 21       | 1A | 10-100     | Rh       | 250                 | 250            | 10 <sup>9</sup>   | 0.3pF    | 5W     | 100DC/125AC   | 1.0DC&AC      |
| TR560 | 2.3      | 14.2     | 1A | 10-50      | Rh       | 200                 | 200            | 10 <sup>12</sup>  | 0.2pF    | 10W    | 100DC/125AC   | 1.0DC&AC      |
| PR560 | 2.3      | 14.2     | 1A | 20-40      | Rh       | 100                 | 600            | 10 <sup>12</sup>  | 0.2pF    | 10W    | 100DC/250AC   | 1.0DC&AC      |
| PR100 | 2.5      | 20.3     | 1A | 20-50      | Rh       | 100                 | 750            | 10 <sup>12</sup>  | 0.2pF    | 10W    | 10DC/250AC    | 1.0DC&AC      |
| PR126 | 2.5      | 20.3     | 1A | 20-50      | Rh       | 100                 | 750            | 10 <sup>12</sup>  | 0.3pF    | 70W    | 200DC/300AC   | 1.5DC&AC      |