

DL9041 六 LED 触发功能

SUNSTAR单片机专用电路 <http://www.icasic.com/> TEL: 0755-83387030 FAX:0755-83376182 E-MAIL:szss20@163.com

FEATURES 功能叙述

输入触发方式: One Shot (负电平)

内置 RC 震荡器

(1)SDL9041-A 32 圈 (2)SDL9041-B 8 圈 (3)SDL9041-E 4 圈 (4)SDL9041-G 16 圈可以长闪 (5)SDL9041-H 16 圈
(6)SDL9041-M 2 圈 (7)SDL9041-L 1 圈

APPLICATION 产品应用

Arcade game system , Toys 2.6HZ

ELECTRICAL CHARACTERISTICS 电气规格 (@VDD=3V unless otherwise specified)

Characteristic	Sym	Min	Typ	Max	Unit	REMARKS
工作电压 Operating Voltage	Vdd	-	3.6	4.5	V	测试电压 3.6V
工作电流 Operating Current	Lop	-	0.4	0.5	mA	R=10K Ω
静态电流 Quiescent Current	Isb	-	1.0	5	uA	加入 INT 无输出前
推动电流 Driving Current	Iol	2	10	20	mA	Vds=1.2V
闪动频率 Flash Frequency	Ftet	-	2.2	-	kHz	$\pm 30\%$
工作温度 Operating Temperature	Temp	0	25	60	$^{\circ}\text{C}$	

APPLICATION DIAGRAM 参考电路

