

RF TRANSFORMERS WIDEBAND

12.5 to 1800 Ω

4 kHz to 1500 MHz

SURFACE MOUNT



ADT



T-KK81



TCM



TC



TX

MODEL NO.	Ω RATIO	FREQUENCY MHz	INSERTION LOSS *			CAPD DATA	CASE STYLE Note B	CONNECTION	PRICE \$
	Note D		3 dB MHz	2 dB MHz	1 dB MHz				Qty. (1-9)
B* ADTT1-1	1	0.3-300	0.3-300	0.4-200	0.5-90		CD542	kr	3.95***
✦ TT1-6-KK81	1	.004-300	.004-300	.02-200	.1-50		KK81	ex	6.95
TT1.5-1-KK81	1.5	.075-500	.075-500	.2-100	1-50		KK81	ex	5.95
TT2.5-6-KK81	2.5	.01-50	.01-50	.025-25	.05-10		KK81	ex	6.45
TT4-1-KK81	3	.05-200	.05-200	.2-50	1-30		KK81	ex	5.95
TT4-1A-KK81	4	0.1-300	0.1-300	0.2-250	0.3-180		KK81	ex	6.95
TT16-1-KK81	16	0.1-45	0.1-45	0.14-35	1-20		KK81	ex	9.95
** TT25-1-KK81	25	.02-30	.02-30	.05-20	.1-10		KK81	ex	9.95
✦ TT1-6	1	.004-300	.004-300	.02-200	.1-50		▽	ex	6.95
TT1.5-1	1.5	.075-500	.075-500	.2-100	1-50		▽	ex	5.95
TT2.5-6	2.5	.01-50	.01-50	.025-25	.05-10		▽	ex	6.45
TT4-1	3	.05-200	.05-200	.2-50	1-30		▽	ex	5.95
TT4-1A	4	0.1-300	0.1-300	0.2-250	0.3-180		▽	ex	6.95
TT16-1	16	0.1-45	0.1-45	0.14-35	1-20		▽	ex	9.95
** TT25-1	25	.02-30	.02-30	.05-20	.1-10		▽	ex	9.95
TTMO25-1	25	.02-30	.02-30	.05-20	.1-10		A03	ey	11.95
TTMO1-1	1	.005-100	.005-100	.01-75	.05-40		A03	ey	11.45
TTMO4-1A	4	0.1-300	0.1-300	0.2-250	0.3-180		A03	ey	13.95
C ADT16-6	16	0.25-105	0.25-105	0.45-75	1-40	ON OUR	CD636	kq	4.95***
NEW ADT4-6	4	0.07-250	.07-250	0.1-220	0.15-150		CD637	kq	4.95***
NEW ADT1-1	1	0.15-400	0.15-400	0.2-200	0.3-100	WEBSITE	CD542	kq	2.95***
T1-1-KK81	1	.15-400	.15-400	.35-200	2-50		KK81	ez	3.25
T1.18-3-KK81	1.18	0.01-250	0.01-250	0.02-200	0.03-50		KK81	ez	5.65
T1-6-KK81	1	.01-150	.01-150	.02-100	.05-50		KK81	ez	5.65
T1.5-1-KK81	1.5	.1-300	.1-300	.2-150	.5-80		KK81	ez	4.45
T1.5-6-KK81	1.5	.02-100	.02-100	.05-50	0.1-25		KK81	ez	5.65
T2-1-2W-KK81	2	5-120	—	—	5-120		KK81	ez	5.95
T2.5-6-KK81	2.5	.01-100	.01-100	.02-50	.05-20		KK81	ez	4.45
T4-1-2W-KK81	4	10-250	—	—	10-250		KK81	ez	5.95
T4-6-KK81	4	.02-200	.02-200	.05-150	.1-100		KK81	ez	5.65
T9-1-KK81	9	.15-200	.15-200	.3-150	2-40		KK81	ez	3.95
T16-1-KK81	16	.3-120	.3-120	.7-80	5-20		KK81	ez	4.45
T36-1-KK81	36	.03-20	.03-20	.05-10	.1-5		KK81	ez	6.95
T1-1H-KK81	1	8-300	8-300	10-200	25-100		KK81	ez	5.95
T9-1H-KK81	9	2-90	2-90	3-75	6-50		KK81	ez	6.45
T16-1H-KK81	16	7-85	7-85	10-65	15-40		KK81	ez	6.45
NEW TCM1-1	1	1.5-500	1.5-500	2.5-400	5.350		DB714	hd	4.45
TC1-1	1	1.5-500	1.5-500	2.5-400	5-350		AT224	hd	4.95
†† TC1-15	1	800-1500	—	350-1500	800-1500		AT224	gw	4.95
TX1-1	1	0.3-400	0.3-400	0.6-200	2-50		TT240	ez	3.50
TX1-R5	1	0.8-500	0.8-500	1.2-350	3.2-180		TT240	ez	3.75
TX1.5-1	1.5	0.25-300	0.25-300	0.3-150	0.5-80		TT240	ez	4.70
TX16-1	16	0.4-120	0.4-120	0.7-80	5-20		TT240	ez	4.70
TX9-1	9	1-200	1-200	1.5-160	3-70		TT240	ez	4.70



INTERNET <http://www.minicircuits.com>

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661

Distribution Centers NORTH AMERICA 800-654-7949 • 417-335-5935 • Fax 417-335-5945 • EUROPE 44-1252-835094 • Fax 44-1252-837010

Surface Mount □ & Plug-In


Style X65



Standard W38



T,TT



TMO, TTMO

MODEL NO.	Ω RATIO Note D	FREQUENCY MHz	INSERTION LOSS *			CAPD DATA	CASE STYLE Note B	CONNECTION	PRICE \$ Qty. (1-9)	
			3 dB MHz	2 dB MHz	1 dB MHz					
C 	T1-1	1	.15-400	.15-400	.35-200	2-50	▽	ez	3.25	
	T1.18-3	1.18	0.01-250	0.01-250	0.02-200	0.03-50	▽	ez	5.65	
	T1-6	1	.01-150	.01-150	.02-100	.05-50	▽	ez	5.65	
	T1.5-1	1.5	.1-300	.1-300	.2-150	.5-80	▽	ez	4.45	
	●●●T1.5-6	1.5	.02-100	.02-100	.05-50	0.1-25	▽	ez	5.65	
	●●●T2-1-2W	2	5-120	—	—	5-120	FOR DATA	▽	ez	5.95
	T2.5-6	2.5	.01-100	.01-100	.02-50	.05-20	▽	ez	4.45	
	T4-1-2W	4	10-250	—	—	10-250	▽	ez	5.95	
	T4-6	4	.02-200	.02-200	.05-150	.1-100	SEE YONI	▽	ez	5.65
	T9-1	9	.15-200	.15-200	.3-150	2-40	▽	ez	3.95	
	T16-1	16	.3-120	.3-120	.7-80	5-20	ON OUR WEBSITE	▽	ez	4.45
	T36-1	36	.03-20	.03-20	.05-10	.1-5	▽	ez	6.95	
	TO-75	1	10-500	—	10-500	40-250	PP94	fa	6.95	
	T1-1H	1	8-300	8-300	10-200	25-100	▽	ez	5.95	
	T9-1H	9	2-90	2-90	3-75	6-50	▽	ez	6.45	
	T16-1H	16	7-85	7-85	10-65	15-40	▽	ez	6.45	
TMO1-02	1	1-800	1-800	2-500	—	A11	fc	9.45		
TMO1-1	1	.15-400	.15-400	.35-200	2-50	A11	fb	6.25		
TMO1.5-1	1.5	.1-300	.1-300	.2-150	.5-80	A11	fb	8.45		
TMO2.5-6	2.5	.01-100	.01-100	.02-50	.05-20	A03	fb	7.95		
TMO4-6	4	.02-200	.02-200	.05-150	.1-100	A03	fb	7.95		
TMO6-1	6	.3-200	.3-200	.5-150	5-50	A11	fb	7.95		
TMO9-1	9	.15-200	.15-200	.3-150	2-40	A11	fb	7.95		
TMO16-1	16	.3-120	.3-120	.7-80	5-20	A11	fb	7.95		

NOTES:

- * FOR B CONFIGURATION:
Typical Amplitude Unbalance: 0.1 dB over 1 dB frequency range; 0.5 dB over entire frequency range.
Typical Phase Unbalance: 1.0° over 1 dB frequency range; 5.0° over entire frequency range.
- * Insertion loss referenced to mid-band loss
- ◆ Insertion loss is specified with input at pin 4 and output at pin 1 with pins 6 & 3 grounded and pins 2 & 5 open.
- ** Below .05 MHz, insertion loss is specified for room temperature and above.
- †† Not DC isolated, insertion loss is measured with input at pin 1, output at pin 6, and pin 3, 4 are grounded.
- Non-hermetic
- ▽ Two case styles available: Plug-in case style X65; Radial lead case style W38.
- *** Price for quantities 10-49.
- A. General Quality Control Procedures, Environmental Specifications, Hi-Rel and MIL description are given in section 0, see "Mini-Circuits Guarantees Quality" article.
- B. Connector types and case mounted options, case finishes are given in section 0, see "Case Styles & Outline Drawings".
- C. Prices and Specifications subject to change without notice.
- D. Impedance ratio= secondary/primary
- 1. Absolute power, voltage and current ratings:
1a. RF input power: all models 0.25W except where noted (● .5W rating; ●●●2W rating)
1b. DC current, 30mA
- 2. For ADT, TC,T,TCM,TT, and TX series, operating temperature range is -20°C to +85°C.

pin connections see case style outline drawings for pin locations

PORT	ex	ey	ez	fa	fb	fc	gw	hd	kq	kr
PRIMARY DOT	4	1	4	1	1	1	1	6	3	3
PRIMARY	6	5	6	2	5	3	6	4	1	1
PRIMARY CT	5	3	—	—	—	—	—	—	—	2
SECONDARY DOT	3	2	3	4	2	2	3	1	4	4
SECONDARY	1	6	1	3	6	4	4	3	6	6
SECONDARY CT	2	4	—	—	—	—	—	—	—	5
GND EXT.	—	—	—	—	—	—	—	—	—	—
CASE GND	—	7.8	—	—	7.8	7.8	—	—	—	—
NOT USED	—	—	2.5	—	3.4	2.5	—	2.5	2.5	—
DEMO BOARD	—	—	—	—	—	—	—	—	TB-42	TB-42

NSN GUIDE

MCL NO.	NSN
T1-1-KK81	5950-01-347-0310
T1-1	5950-01-128-3745
T1-1-X65	5950-01-327-5916
T1-1H	5950-01-409-2785
T9-1	5950-01-105-8153
T16-1	5950-01-094-7439
T16-1-X65	5950-01-272-2297
TMO1-1	5950-01-213-3735
TMO2.5-6	5950-01-215-4038
TMO4-6	5950-01-132-8102
TMO6-1	5950-01-364-7803
TMO9-1	5950-01-141-0174
TMO16-1	5950-01-138-4593
TT1-6-X65	5950-01-272-2298
TT4-1A	5950-01-331-7777
TTMO25-T	5950-01-415-7145

SUNSTAR 商斯达实业集团是集研发、生产、工程、销售、代理经销、技术咨询、信息服务等为一体的高科技企业，是专业高科技电子产品生产厂家，是具有 10 多年历史的专业电子元器件供应商，是中国最早和最大的仓储式连锁规模经营大型综合电子零部件代理分销商之一，是一家专业代理和分销世界各大品牌 IC 芯片和电子元器件的连锁经营综合性国际公司，专业经营进口、国产名厂名牌电子元件，型号、种类齐全。在香港、北京、深圳、上海、西安、成都等全国主要电子市场设有直属分公司和产品展示展销窗口门市部专卖店及代理分销商，已在全国范围内建成强大统一的供货和代理分销网络。我们专业代理经销、开发生产电子元器件、集成电路、传感器、微波光电元器件、工控机/DOC/DOM 电子盘、专用电路、单片机开发、MCU/DSP/ARM/FPGA 软件硬件、二极管、三极管、模块等，是您可靠的一站式现货配套供应商、方案提供商、部件功能模块开发配套商。商斯达实业公司拥有庞大的资料库，有数位毕业于著名高校——有中国电子工业摇篮之称的西安电子科技大学（西军电）并长期从事国防尖端科技研究的高级工程师为您精挑细选、量身订做各种高科技电子元器件，并解决各种技术问题。

微波光电部专业代理经销高频、微波、光纤、光电元器件、组件、部件、模块、整机；电磁兼容元器件、材料、设备；微波 CAD、EDA 软件、开发测试仿真工具；微波、光纤仪器仪表。欢迎国外高科技微波、光纤厂商将优秀产品介绍到中国、共同开拓市场。长期大量现货专业批发高频、微波、卫星、光纤、电视、CATV 器件：晶振、VCO、连接器、PIN 开关、变容二极管、开关二极管、低噪晶体管、功率电阻及电容、放大器、功率管、MMIC、混频器、耦合器、功分器、振荡器、合成器、衰减器、滤波器、隔离器、环行器、移相器、调制解调器；光电子器件和组件：红外发射管、红外接收管、光电开关、光敏管、发光二极管和发光二极管组件、半导体激光二极管和激光器组件、光电探测器和光接收组件、光发射接收模块、光纤激光器和光放大器、光调制器、光开关、DWDM 用光发射和接收器件、用户接入系统光收发器件与模块、光纤连接器、光纤跳线/尾纤、光衰减器、光纤适配器、光隔离器、光耦合器、光环行器、光复用器/转换器；无线收发芯片和模组、蓝牙芯片和模组。

更多产品请看本公司产品专用销售网站：

商斯达中国传感器科技信息网：<http://www.sensor-ic.com/>

商斯达工控安防网：<http://www.pc-ps.net/>

商斯达电子元器件网：<http://www.sunstare.com/>

商斯达微波光电产品网：[HTTP://www.rfoe.net/](http://www.rfoe.net/)

商斯达消费电子产品网：<http://www.icasic.com/>

商斯达实业科技产品网：<http://www.sunstars.cn/> 微波元器件销售热线：

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-82884100 83397033 83396822 83398585

传真：0755-83376182 (0) 13823648918 MSN: SUNS8888@hotmail.com

邮编：518033 E-mail:szss20@163.com QQ: 195847376

深圳赛格展销部：深圳华强北路赛格电子市场 2583 号 电话：0755-83665529 25059422

技术支持：0755-83394033 13501568376

欢迎索取免费详细资料、设计指南和光盘；产品凡多，未能尽录，欢迎来电查询。

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL: 010-81159046 82615020 13501189838 FAX: 010-62543996

上海分公司：上海市北京东路 668 号上海赛格电子市场 D125 号

TEL: 021-28311762 56703037 13701955389 FAX: 021-56703037

西安分公司：西安高新开发区 20 所(中国电子科技集团导航技术研究所)

西安劳动南路 88 号电子商城二楼 D23 号

TEL: 029-81022619 13072977981 FAX:029-88789382