

Power Supplies

FAK Series

AC Input
Single Output, General-Purpose


FEATURES

- Rail mountable. Small open frame(cover is optional).
- Low cost.
- These low noise power supplies are FCC class B compliant.

PART NUMBERS AND RATINGS

Output voltage (V)	15W type		25W type		50W type	
	Current (A)	Part No.	Current (A)	Part No.	Current (A)	Part No.
5	3	FAK05-3R0	5	FAK05-5R0	10	FAK05-10R
12	1.3	FAK12-1R3	2.1	FAK12-2R1	4.2	FAK12-4R2
15	1	FAK15-1R0	1.7	FAK15-1R7	3.4	FAK15-3R4
24	0.7	FAK24-0R7	1.1	FAK24-1R1	2.1	FAK24-2R1

Output voltage (V)	100W type		150W type	
	Current (A)	Part No.	Current (A)	Part No.
5	20	FAK05-20R	30	FAK05-30R
12	8.3	FAK12-8R3	12	FAK12-12R
15	6.6	FAK15-6R6	10	FAK15-10R
24	4.2	FAK24-4R2	6	FAK24-6R0
48	2	FAK48-2R0	3	FAK48-3R0



Power Supplies

FAK Series

AC Input

Single Output, General-Purpose

SPECIFICATIONS

15W TYPE

Part No.		FAK05-3R0*1	FAK12-1R3	FAK15-1R0	FAK24-0R7
Output voltage, current*2		5V • 3A	12V • 1.3A	15V • 1A	24V • 0.7A
Maximum output power	W	15	15.6	15	16.8
Input requirements					
Input voltage Eac	V	85 to 132[Rating:100-120](DC.110 to 175V available)			
Input frequency	Hz	47 to 66[Rating:50-60](Single phase)			
Input current	A	0.4max.[AC.100/120V]			
Fuse rating	A	2[Internal]			
Surge current *3	A	18-22max.[AC.100-120V, 25°C, output rating, cold start]			
Leakage current	mA	0.5max.[25°C, input and output ratings]			
Efficiency	%	72typ.[25°C, input and output ratings]			
Output characteristics					
Output voltage	V	5	12	15	24
Voltage variable range	V	4.5 to 5.5	10.8 to 13.2	13.5 to 16.5	21.6 to 26.4
Maximum output current*2	A	3	1.3	1	0.7
Overvoltage threshold	V	—	—	—	—
Overcurrent threshold	A	3.3 to 5	1.4 to 2.3	1.1 to 2	0.8 to 1.4
Voltage stability	Input variation	%	±1max.(±0.3typ.)[Within the input voltage range]		
	Load variation	%	±1.5max.(±0.6typ.)[10 to 100% load]		
	Temperature variation	%	±1max.(±0.3typ.)[0 to +60°C]		
	Drift	%	1max.[25°C, input and output ratings, after input voltage ON for 30min to 8h]		
	Dynamic load	%/ms	±4max./1max.[50 to 100% sudden load change]		
Ripple Ep-p	mV	60max.	80max.	80max.	100max.
Ripple noise Ep-p	mV	120max.			
Start up time	ms	100max.			
Hold up time	ms	20min.			
Accessory equipment					
Operation indicator		LED illuminates when voltage output is ON.			
Overvoltage protection		None			
Overcurrent protection		Fixed threshold, higher overcurrent detection point at low load, automatic recovery.			
Remote ON-OFF		None			
Remote sensing		None			
Current balance		None			
Standards					
Safety standards		UL1950D3, CSA ELECTRICAL BULLETIN No.1402 approved.			
Noise terminal voltage		FCC class B compliant.			
Construction					
External dimensions H×W×L	mm	20×70×95 With cover(Option)*4: 23×70×95			
Weight	g	200max. With cover(Option): 250max.			
Mounting method		Can be attached to 2 sides.			
Case material		Frame: Aluminum Cover(Option: 3JC0ZB145-FAK15CA):Steel			

*1 Output may fail to come on when operated in series.

*2 Current rating(maximum output current) is determined for 0 to +50°C. Derating is required when used outside this temperature range.

*3 The surge current suppression element is a power thermistor.

*4 Derating is required when the optional cover is attached.

Power Supplies

FAK Series

AC Input

Single Output, General-Purpose

SPECIFICATIONS

25W TYPE

Part No.		FAK05-5R0* ¹	FAK12-2R1	FAK15-1R7	FAK24-1R1
Output voltage, current* ²		5V • 5A	12V • 2.1A	15V • 1.7A	24V • 1.1A
Maximum output power	W	25	25.2	25.5	26.4
Input requirements					
Input voltage Eac	V	85 to 132[Rating: 100-120](DC.110 to 175V available)			
Input frequency	Hz	47 to 66[Rating: 50-60](Single phase)			
Input current	A	0.65max.[AC.100/120V]			
Fuse rating	A	2.5[Internal]			
Surge current * ³	A	36-43max.[AC.100-120V, 25°C, output rating, cold start]			
Leakage current	mA	0.5max.[25°C, input and output ratings]			
Efficiency	%	70typ.[25°C, input and output ratings]			
Output characteristics					
Output voltage	V	5	12	15	24
Voltage variable range	V	4.5 to 5.5	10.8 to 13.2	13.5 to 16.5	21.6 to 26.4
Maximum output current* ²	A	5	2.1	1.7	1
Overvoltage threshold	V	6 to 6.9	13.7 to 15.7	17 to 19	27 to 30.5
Overcurrent threshold	A	5.5 to 7.5	2.3 to 3.3	1.9 to 2.8	1.2 to 1.8
Voltage stability	Input variation	%	±1max.(±0.3typ.)[Within the input voltage range]		
	Load variation	%	±1.5max.(±0.6typ.)[10 to 100% load]		
	Temperature variation	%	±1.5max.(±0.3typ.)[0 to +60°C]		
	Drift	%	0.5max.[25°C, input and output ratings, after input voltage ON for 30min to 8h]		
	Dynamic load	%/ms	±4max./1max.[50 to 100% sudden load change]		
Ripple Ep-p	mV	80max.	80max.	80max.	100max.
Ripple noise Ep-p	mV	120max.	190max.	220max.	310max.
Start up time	ms	100max.			
Hold up time	ms	20min.			
Accessory equipment					
Operation indicator		LED illuminates when voltage output is ON.			
Overvoltage protection		Voltage shielding type, recovers upon reset, set value fixed.			
Overcurrent protection		Fixed threshold, higher overcurrent detection point at low load, automatic recovery.			
Remote ON-OFF		None			
Remote sensing		None			
Current balance		None			
Standards					
Safety standards		UL1950D3, CSA ELECTRICAL BULLETIN No.1402 approved.			
Noise terminal voltage		FCC class B compliant.			
Construction					
External dimensions H×W×L	mm	25×70×115 With cover(Option)* ⁴ : 28.5×70×115			
Weight	g	220max. With cover(Option): 300max.			
Mounting method		Can be attached to 2 sides.			
Case material		Frame: Aluminum Cover(Option: 2JC0ZB146-FAK25CA):Steel			

*¹ Output may fail to come on when operated in series.*² Current rating(maximum output current) is determined for 0 to +50°C. Derating is required when used outside this temperature range.*³ The surge current suppression element is a power thermistor.*⁴ Derating is required when the optional cover is attached.

Power Supplies

FAK Series

AC Input

Single Output, General-Purpose

SPECIFICATIONS

50W TYPE

Part No.		FAK05-10R	FAK12-4R2	FAK15-3R4	FAK24-2R1
Output voltage, current* ¹		5V • 10A	12V • 4.2A	15V • 3.4A	24V • 2.1A
Maximum output power	W	50	50.4	51	50.4
Input requirements					
Input voltage Eac	V	85 to 132[Rating: 100-120](DC.110 to 175V available)			
Input frequency	Hz	47 to 66[Rating: 50-60](Single phase)			
Input current	A	1.2max.[AC.100/120V]			
Fuse rating	A	3.15[Internal]			
Surge current * ²	A	36-43max.[AC.100-120V, 25°C, output rating, cold start]			
Leakage current	mA	0.5max.[25°C, input and output ratings]			
Efficiency	%	80typ.[25°C, input and output ratings]			
Output characteristics					
Output voltage	V	5	12	15	24
Voltage variable range	V	4.5 to 5.5	10.8 to 13.2	13.5 to 16.5	21.6 to 26.4
Maximum output current* ¹	A	10	4.2	3.4	2.1
Overvoltage threshold	V	6 to 6.9	13.7 to 15.7	17 to 19	27 to 30.5
Overcurrent threshold	A	10.5 to 12	4.4 to 5.1	3.6 to 4.1	2.2 to 2.6
Voltage stability	Input variation	%	±1max.(±0.3typ.)[Within the input voltage range]		
	Load variation	%	±1.5max.(±0.6typ.)[10 to 100% load]		
	Temperature variation	%	±1max.(±0.3typ.)[0 to +60°C]		
	Drift	%	0.5max.[25°C, input and output ratings, after input voltage ON for 30min to 8h]		
	Dynamic load	%/ms	±4max./1max.[50 to 100% sudden load change]		
Ripple Ep-p	mV	60max.	80max.	80max.	100max.
Ripple noise Ep-p	mV	Output voltage×1%+70max.[50MHz max. including ripple]			
Start up time	ms	100max.			
Hold up time	ms	20min.			
Accessory equipment					
Operation indicator		LED illuminates when voltage output is ON.			
Overvoltage protection		Voltage shielding type, recovers upon reset, set value fixed.			
Overcurrent protection		Fixed current and voltage threshold type, automatic recovery, set value fixed.			
Remote ON-OFF		None			
Remote sensing		None			
Current balance		None			
Standards					
Safety standards		UL1950D3, CSA ELECTRICAL BULLETIN No.1402 approved.			
Noise terminal voltage		FCC class B compliant.			
Construction					
External dimensions H×W×L	mm	25×95×130 With cover(Option)* ³ : 28.5×95×130			
Weight	g	300max. With cover(Option): 400max.			
Mounting method		Can be attached to 2 sides.			
Case material		Frame: Aluminum Cover(Option: 2JC00B147-FAK50CA):Steel			

*1 Current rating(maximum output current) is determined for 0 to +50°C. Derating is required when used outside this temperature range.

*2 The surge current suppression element is a power thermistor.

*3 Derating is required when the optional cover is attached.

Power Supplies

FAK Series

AC Input

Single Output, General-Purpose

SPECIFICATIONS

100W TYPE

Part No.		FAK05-20R	FAK12-8R3	FAK15-6R6	FAK24-4R2	FAK48-2R0
Output voltage, current*		5V • 20A	12V • 8.3A	15V • 6.6A	24V • 4.2A	48V • 2A
Maximum output power	W	100	99.6	99	100.8	96
Input requirements						
Input voltage Eac	V	85 to 132[Rating: 100-120]				
Input frequency	Hz	47 to 66[Rating: 50-60](Single phase)				
Input current	A	2.5max.[100/120V]				
Fuse rating	A	5[Internal]				
Surge current	A	25max.[100/120V, 1st surge current, reset after roughly 30s min.]				
Leakage current	mA	0.5max.[100/120V]				
Efficiency	%	82typ.	84typ.	85typ.	86typ.	87typ.
Output characteristics						
Output voltage	V	5	12	15	24	48
Voltage variable range	V	4.5 to 5.5	10.8 to 13.2	13.5 to 16.5	21.6 to 26.4	43.2 to 52.8
Maximum output current*	A	20	8.3	6.6	4.2	2
Overvoltage threshold	V	6 to 6.9	13.7 to 15.7	17 to 19	27 to 30.5	53.5 to 60
Overcurrent threshold	A	21 to 24	8.7 to 10	7 to 8	4.4 to 5.2	2.1 to 2.4
Voltage stability	Input variation	%	2max.(1typ.)[Within the input voltage range]			
	Load variation	%	2max.(1typ.)[10 to 100% load]			
	Temperature variation	%	2max.(1typ.)[0 to +50°C]			
	Drift	%	0.5max.(0.1typ.)[25°C, input and output ratings, after input voltage ON for 30min to 8h]			
	Dynamic load	%/ms	±4max./1max.[50 to 100% sudden load change]			
Ripple Ep-p	mV	60max.	80max.	80max.	100max.	200max.
Ripple noise Ep-p	mV	120max.	190max.	220max.	310max.	400max.
Start up time	ms	200max.[100V]				
Hold up time	ms	20min.[100V]				
Accessory equipment						
Operation indicator		LED(green) illuminates when voltage output is ON.				
Overvoltage protection		Voltage shielding type, recovers upon reset.				
Overcurrent protection		Fixed current and voltage threshold type, automatic recovery.				
Remote ON-OFF		None				
Remote sensing		Yes				
Output voltage external variable function		None				
Standards						
Safety standards		UL1950, CSA ELECTRICAL BULLETIN No.1402C approved.				
Noise terminal voltage		FCC class B compliant.				
Construction						
External dimensions H×W×L	mm	35×95×165 With cover(Option): 40×95×165				
Weight	g	600max.				
Mounting method		Can be attached to 2 sides.				
Case material		Frame: Aluminum Cover(Option: 2JC0ZB390-FAK100CA):Steel				

* Current rating(maximum output current) is determined for 0 to +50°C. Derating is required when used outside this temperature range.

Power Supplies

FAK Series

AC Input

Single Output, General-Purpose

SPECIFICATIONS

150W TYPE

Part No.		FAK05-30R	FAK12-12R	FAK15-10R	FAK24-6R0	FAK48-3R0
Output voltage, current*		5V • 30A	12V • 12A	15V • 10A	24V • 6A	48V • 3A
Maximum output power	W	150	144	150	144	144
Input requirements						
Input voltage Eac	V	85 to 132[Rating: 100-120]				
Input frequency	Hz	47 to 66[Rating: 50-60](Single phase)				
Input current	A	3.5max.[100/120V]				
Fuse rating	A	6.3[Internal]				
Surge current	A	25max.[100/120V, 1st surge current, reset after roughly 30s min.]				
Leakage current	mA	0.5max.[100/120V]				
Efficiency	%	82typ.	84typ.	85typ.	86typ.	88typ.
Output characteristics						
Output voltage	V	5	12	15	24	48
Voltage variable range	V	4.5 to 5.5	10.8 to 13.2	13.5 to 16.5	21.6 to 26.4	43.2 to 52.8
Maximum output current*	A	30	12	10	6	3
Overvoltage threshold	V	6 to 6.9	13.7 to 15.7	17 to 19	27 to 30.5	53.5 to 60
Overcurrent threshold	A	32 to 36	13 to 15	11 to 13	6.3 to 7.5	3.3 to 3.7
Voltage stability	Input variation	%	2max.(1typ.)[Within the input voltage range]			
	Load variation	%	2max.(1typ.)[10 to 100% load]			
	Temperature variation	%	2max.(1typ.)[0 to +50°C]			
	Drift	%	0.5max.(0.1typ.)[25°C, input and output ratings, after input voltage ON for 30min to 8h]			
	Dynamic load	%/ms	±4max./1max.[50 to 100% sudden load change]			
Ripple Ep-p	mV	60max.	80max.	80max.	100max.	200max.
Ripple noise Ep-p	mV	120max.	190max.	220max.	310max.	400max.
Start up time	ms	200max.[100V]				
Hold up time	ms	20min.[100V]				
Accessory equipment						
Operation indicator		LED (green) illuminates when voltage output is ON.				
Overvoltage protection		Voltage shielding type, recovers upon reset(interval approx. 40s).				
Overcurrent protection		Fixed current and voltage threshold type, automatic recovery.				
Remote ON-OFF		None				
Remote sensing		Yes				
Output voltage external variable function		None				
Standards						
Safety standards		UL1950, CSA ELECTRICAL BULLETIN No.1402C approved.				
Noise terminal voltage		FCC class B compliant.				
Construction						
External dimensions H×W×L	mm	40×95×200 With cover(Option): 45×95×200				
Weight	kg	1max.				
Mounting method		Can be attached to 2 sides.				
Case material		Frame: Aluminum Cover(Option: 2JC0ZB391-FAK150CA):Steel				

* Current rating(maximum output current) is determined for 0 to +50°C. Derating is required when used outside this temperature range.

Power Supplies


FAK Series

AC Input


Single Output, General-Purpose

TERMINAL DESIGNATIONS AND FUNCTIONS


15W, 25W TYPE




50W TYPE



100W TYPE



150W TYPE



Terminal No. 1: Frame ground terminal($\perp$)

Terminal No. 2: AC input terminals(L, N)

Terminal No. 3: DC output terminals(+, -)

Terminal No. 4: Output voltage adjustment trim

Terminal No. 5: Ground terminal(G)

Terminal No. 6: Remote sensing terminals(+S, -S)

Terminal No. 7: Operation indicator LED

SUNSTAR 商斯达实业集团是集研发、生产、工程、销售、代理经销、技术咨询、信息服务等为一体的高科技企业，是专业高科技电子产品生产厂家，是具有 10 多年历史的专业电子元器件供应商，是中国最早和最大的仓储式连锁规模经营大型综合电子零部件代理分销商之一，是一家专业代理和分销世界各大品牌 IC 芯片和电子元器件的连锁经营综合性国际公司，专业经营进口、国产名厂名牌电子元件，型号、种类齐全。在香港、北京、深圳、上海、西安、成都等全国主要电子市场设有直属分公司和产品展示展销窗口门市部专卖店及代理分销商，已在全国范围内建成强大统一的供货和代理分销网络。我们专业代理经销、开发生产电子元器件、集成电路、传感器、微波光电元器件、工控机/DOC/DOM 电子盘、专用电路、单片机开发、MCU/DSP/ARM/FPGA 软件硬件、二极管、三极管、模块等，是您可靠的一站式现货配套供应商、方案提供商、部件功能模块开发配套商。商斯达实业公司拥有庞大的资料库，有数位毕业于著名高校——有中国电子工业摇篮之称的西安电子科技大学（西军电）并长期从事国防尖端科技研究的高级工程师为您精挑细选、量身订做各种高科技电子元器件，并解决各种技术问题。

微波光电部专业代理经销高频、微波、光纤、光电元器件、组件、部件、模块、整机；电磁兼容元器件、材料、设备；微波 CAD、EDA 软件、开发测试仿真工具；微波、光纤仪器仪表。欢迎国外高科技微波、光纤厂商将优秀产品介绍到中国、共同开拓市场。长期大量现货专业批发高频、微波、卫星、光纤、电视、CATV 器件：晶振、VCO、连接器、PIN 开关、变容二极管、开关二极管、低噪晶体管、功率电阻及电容、放大器、功率管、MMIC、混频器、耦合器、功分器、振荡器、合成器、衰减器、滤波器、隔离器、环行器、移相器、调制解调器；光电子器件和组件：红外发射管、红外接收管、光电开关、光敏管、发光二极管和发光二极管组件、半导体激光二极管和激光器组件、光电探测器和光接收组件、光发射接收模块、光纤激光器和光放大器、光调制器、光开关、DWDM 用光发射和接收器件、用户接入系统光收发器件与模块、光纤连接器、光纤跳线/尾纤、光衰减器、光纤适配器、光隔离器、光耦合器、光环行器、光复用器/转换器；无线收发芯片和模组、蓝牙芯片和模组。

更多产品请看本公司产品专用销售网站：

商斯达微波光电产品网：[HTTP://www.rfoe.net/](http://www.rfoe.net/)

商斯达中国传感器科技信息网：<http://www.sensor-ic.com/>

商斯达工控安防网：<http://www.pc-ps.net/>

商斯达电子元器件网：<http://www.sunstare.com/>

商斯达消费电子产品网：<http://www.icasic.com/>

商斯达实业科技产品网：<http://www.sunstars.cn/> 射频微波光电元器件销售热线：

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-83396822 83397033 83398585 82884100

传真：0755-83376182 (0) 13823648918 MSN: SUNS8888@hotmail.com

邮编：518033 E-mail:szss20@163.com QQ: 195847376

深圳赛格展销部：深圳华强北路赛格电子市场 2583 号 电话：0755-83665529 25059422

技术支持：0755-83394033 13501568376

欢迎索取免费详细资料、设计指南和光盘；产品凡多，未能尽录，欢迎来电查询。

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL: 010-81159046 82615020 13501189838 FAX: 010-62543996

上海分公司：上海市北京东路 668 号上海赛格电子市场 D125 号

TEL: 021-28311762 56703037 13701955389 FAX: 021-56703037

西安分公司：西安高新开发区 20 所(中国电子科技集团导航技术研究所)

西安劳动南路 88 号电子商城二楼 D23 号

TEL: 029-81022619 13072977981 FAX:029-88789382