

Power Supplies

FMP, FMP-B Series

AC Input
Single Output, General-Purpose


FEATURES

- Economical due to plastic case.
- FMP-B has pin terminals for board mounting.
- These low noise power supplies are FCC class B compliant.

PART NUMBERS AND RATINGS

Output voltage(V)	3W type		10W type	
	Current(A)	Part No.	Current(A)	Part No.
5	0.06 to 0.6	FMP05-R60	0.2 to 2	FMP05-2R0
		FMP05-R60B		FMP05-2R0B
12	0.02 to 0.25	FMP12-R25	0.08 to 0.85	FMP12-R85
		FMP12-R25B		FMP12-R85B
15	0.02 to 0.2	FMP15-R20	0.07 to 0.7	FMP15-R70
		FMP15-R20B		FMP15-R70B
24	0.01 to 0.13	FMP24-R13	0.04 to 0.45	FMP24-R45
		FMP24-R13B		FMP24-R45B

TERMINAL DESIGNATIONS AND FUNCTIONS



- Terminal No. 1: DC output terminals(+, -)
Connect to load.
- Terminal No. 2: No connection(NC)
Unconnected terminal. This should not be connected.
- Terminal No. 3: Ground terminal($\perp$)
For input line.
- Terminal No. 4: AC input terminals(L, N, AC INPUT)
Connect to AC.100 to 120V single phase power supply.



Power Supplies

FMP, FMP-B Series

AC Input

Single Output, General-Purpose

SPECIFICATIONS

3W TYPE

Part No.		FMP05-R60* ¹ FMP05-R60B* ¹	FMP12-R25 FMP12-R25B	FMP15-R20 FMP15-R20B	FMP24-R13 FMP24-R13B
Output voltage, current * ²		5V • 0.6A	12V • 0.25A	15V • 0.2A	24V • 0.13A
Maximum output power	W	3	3	3	3.1
Input requirements					
Input voltage Eac	V	85 to 132[Rating: 100-120]			
Input frequency	Hz	47 to 440[Single phase]			
Input current	A	0.08typ.[85V, 25°C, input and output ratings](Output rating: 0.1max.)			
Surge current	A	16max.[25°C, input and output ratings, cold start]			
Leakage current	mA	0.5max.[25°C, input and output ratings]			
Efficiency	%	68typ.	70typ.	70typ.	74typ.
Output characteristics					
Output voltage	V	5	12	15	24
Voltage variable range	V	4.5 to 5.5	10.8 to 13.2	13.5 to 16.5	21.6 to 26.4
Maximum output current* ²	A	0.6	0.25	0.2	0.13
Minimum output current* ³	A	0.06	0.02	0.02	0.01
Overcurrent threshold	A	0.7 to 1.2	0.3 to 0.5	0.25 to 0.4	0.15 to 0.3
Voltage stability	Input variation	%	0.1typ.[Within the input voltage range]		
	Load variation	%	0.8typ.[10 to 100% load]		
	Temperature variation	%	1typ.[0 to +50°C]		
	Drift	%	1max.[25°C, input and output ratings, after input voltage ON for 30min to 8h]		
	Dynamic load	%/ms	±4max./1max.[50 to 100% sudden load change]		
Ripple Ep-p	mV	50max.	80max.	80max.	100max.
Ripple noise Ep-p	mV	100max.	150max.	150max.	150max.
Start up time	ms	100max.			
Hold up time	ms	20min.			
Accessory equipment					
Operation indicator		None			
Overvoltage protection		Uses overvoltage prevention* ⁴			
Overcurrent protection		Fixed voltage threshold type, automatic recovery.			
Remote ON-OFF		None			
Remote sensing		None			
Output voltage external variable function		None			
Standards					
Safety standards		UL478, CSA ELECTRICAL BULLETIN No.1402 approved.			
Noise terminal voltage		FCC class B compliant.			
Construction					
External dimensions H×W×L	mm	19×55×50[Except input and output terminals]			
Weight	g	80max.			
Mounting method		Can be attached to 1 side.			
Case material		Nonflammable resin			
Input and output cables		None			

*1 Output may fail to come on when operated in series.

*2 Current rating(maximum output current) is determined for 0 to +50°C. Derating is required when used outside this temperature range.

*3 The output load variation is determined within the range set by the minimum output current and the maximum output current. Nominal values might possibly not be satisfied when output is below the minimum output current.

*4 Although there is no built-in overvoltage protection circuit, the overvoltage prevention method is used for circuit design, thereby preventing overvoltage.

Power Supplies

FMP, FMP-B Series

AC Input

Single Output, General-Purpose

SPECIFICATIONS

10W TYPE

Part No.			FMP05-2R0*1 FMP05-2R0B*1	FMP12-R85 FMP12-R85B	FMP15-R70 FMP15-R70B	FMP24-R45 FMP24-R45B
Output voltage, current*2			5V • 2A	12V • 0.85A	15V • 0.7A	24V • 0.45A
Maximum output power		W	10	10.2	10.5	10.8
Input requirements						
Input voltage Eac		V	85 to 132[Rating: 100-120]			
Input frequency		Hz	47 to 440[Single phase]			
Input current		A	0.25typ.[85V, 25°C, input and output ratings](Output ratings: 0.35max.)			
Surge current		A	16max.[25°C, input and output ratings, cold start]			
Leakage current		mA	0.5max.[25°C, input and output ratings]			
Efficiency		%	75typ.	78typ.	78typ.	81typ.
Output characteristics						
Output voltage		V	5	12	15	24
Voltage variable range		V	4.5 to 5.5	10.8 to 13.2	13.5 to 16.5	21.6 to 26.4
Maximum output current*2		A	2	0.85	0.7	0.45
Minimum output current*3		A	0.2	0.08	0.07	0.04
Overcurrent threshold		A	2.2 to 3.3	0.9 to 1.4	0.75 to 1.2	0.5 to 0.8
Voltage stability	Input variation	%	0.1typ.[Within the input voltage range]			
	Load variation	%	0.8typ.[10 to 100% load]			
	Temperature variation	%	1typ.[0 to +50°C]			
	Drift	%	1max.[25°C, input and output ratings, after input voltage ON for 30min to 8h]			
	Dynamic load	%/ms	±4max./1max.[50 to 100% sudden load change]			
Ripple Ep-p		mV	50max.	80max.	80max.	100max.
Ripple noise Ep-p		mV	100max.	150max.	150max.	150max.
Start up time		ms	100max.			
Hold up time		ms	20min.			
Accessory equipment						
Operation indicator			None			
Overvoltage protection			Uses overvoltage prevention*4			
Overcurrent protection			Fixed voltage threshold type, automatic recovery.			
Remote ON-OFF			None			
Remote sensing			None			
Output voltage external function			None			
Standards						
Safety standards			UL478, CSA ELECTRICAL BULLETIN No.1402 approved.			
Noise terminal voltage			FCC class B compliant.			
Construction						
External dimensions H×W×L		mm	19×55×80[Except input and output terminals]			
Weight		g	100max.			
Mounting method			Can be attached to 1 side.			
Case material			Nonflammable resin			
Input and output cables			None			

*1 Output may fail to come on when operated in series.

*2 Current rating(maximum output current) is determined for 0 to +50°C. Derating is required when used outside this temperature range.

*3 The output load variation is determined within the range set by the minimum output current and the maximum output current. Nominal values might possibly not be satisfied when output is below the minimum output current.

*4 Although there is no built-in overvoltage protection circuit, the overvoltage prevention method is used for circuit design, thereby preventing overvoltage.

SUNSTAR 商斯达实业集团是集研发、生产、工程、销售、代理经销、技术咨询、信息服务等为一体的高科技企业，是专业高科技电子产品生产厂家，是具有 10 多年历史的专业电子元器件供应商，是中国最早和最大的仓储式连锁规模经营大型综合电子零部件代理分销商之一，是一家专业代理和分销世界各大品牌 IC 芯片和电子元器件的连锁经营综合性国际公司，专业经营进口、国产名厂名牌电子元件，型号、种类齐全。在香港、北京、深圳、上海、西安、成都等全国主要电子市场设有直属分公司和产品展示展销窗口门市部专卖店及代理分销商，已在全国范围内建成强大统一的供货和代理分销网络。我们专业代理经销、开发生产电子元器件、集成电路、传感器、微波光电元器件、工控机/DOC/DOM 电子盘、专用电路、单片机开发、MCU/DSP/ARM/FPGA 软件硬件、二极管、三极管、模块等，是您可靠的一站式现货配套供应商、方案提供商、部件功能模块开发配套商。商斯达实业公司拥有庞大的资料库，有数位毕业于著名高校——有中国电子工业摇篮之称的西安电子科技大学（西军电）并长期从事国防尖端科技研究的高级工程师为您精挑细选、量身订做各种高科技电子元器件，并解决各种技术问题。

微波光电部专业代理经销高频、微波、光纤、光电元器件、组件、部件、模块、整机；电磁兼容元器件、材料、设备；微波 CAD、EDA 软件、开发测试仿真工具；微波、光纤仪器仪表。欢迎国外高科技微波、光纤厂商将优秀产品介绍到中国、共同开拓市场。长期大量现货专业批发高频、微波、卫星、光纤、电视、CATV 器件：晶振、VCO、连接器、PIN 开关、变容二极管、开关二极管、低噪晶体管、功率电阻及电容、放大器、功率管、MMIC、混频器、耦合器、功分器、振荡器、合成器、衰减器、滤波器、隔离器、环行器、移相器、调制解调器；光电子器件和组件：红外发射管、红外接收管、光电开关、光敏管、发光二极管和发光二极管组件、半导体激光二极管和激光器组件、光电探测器和光接收组件、光发射接收模块、光纤激光器和光放大器、光调制器、光开关、DWDM 用光发射和接收器件、用户接入系统光收发器件与模块、光纤连接器、光纤跳线/尾纤、光衰减器、光纤适配器、光隔离器、光耦合器、光环行器、光复用器/转换器；无线收发芯片和模组、蓝牙芯片和模组。

更多产品请看本公司产品专用销售网站：

商斯达微波光电产品网：[HTTP://www.rfoe.net/](http://www.rfoe.net/)

商斯达中国传感器科技信息网：<http://www.sensor-ic.com/>

商斯达工控安防网：<http://www.pc-ps.net/>

商斯达电子元器件网：<http://www.sunstare.com/>

商斯达消费电子产品网：<http://www.icasic.com/>

商斯达实业科技产品网：<http://www.sunstars.cn/> 射频微波光电元器件销售热线：

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-83396822 83397033 83398585 82884100

传真：0755-83376182 (0) 13823648918 MSN: SUNS8888@hotmail.com

邮编：518033 E-mail:szss20@163.com QQ: 195847376

深圳赛格展销部：深圳华强北路赛格电子市场 2583 号 电话：0755-83665529 25059422

技术支持：0755-83394033 13501568376

欢迎索取免费详细资料、设计指南和光盘；产品凡多，未能尽录，欢迎来电查询。

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL: 010-81159046 82615020 13501189838 FAX: 010-62543996

上海分公司：上海市北京东路 668 号上海赛格电子市场 D125 号

TEL: 021-28311762 56703037 13701955389 FAX: 021-56703037

西安分公司：西安高新开发区 20 所(中国电子科技集团导航技术研究所)

西安劳动南路 88 号电子商城二楼 D23 号

TEL: 029-81022619 13072977981 FAX:029-88789382