

PREAMPLIFIER AND DOLBY B TYPE NOISE REDUCTION SYSTEM

■ GENERAL DESCRIPTION


The NJM2085 is a monolithic BiCMOS IC designed for use in the car stereo cassette player system. The audio signal system for cassette player can be realized very easy, as the device includes two channel low noise preamplifiers. Dolby B type noise reduction decoders and an audiomusic sensor.

(note) Dolby and the double-D symbol are trade marks of Dolby Laboratories Licensing Corporation San Francisco. CA94103-4813, USA.

This device available only to licensees of Dolby Lab.

Licensing and application information may be obtained from Dolby Lab.

■ PACKAGE OUTLINE



NJM2085M

■ FEATURES

- Operating Voltage (8~10.5V)
- The dual preamplifier contains mute, auto-reverse matel/norm, facilities for application of low level signal in applications requiring very low noise performances. Each channel consists of a 36dB fixed gain amplifier, having switchable input for forward/reverse, allows magnetic heads connection directly to ground and operational amplifier for switching the external equalizing networks.
- The audio music sensor detects the interprogram space and then the starting point of musical program.
- Dolby B Type Noise Reduction Decoders require few external components.
- Package Outline SDMP30
- Bipolar Technology

■ FUNCTIONS

- Low noise head preamplifiers
- Mute and auto-reverse functions
- Internal switches for equalization
- 2 channel Dolby B Type Noise Reduction Decoders
- Audio music sensor

■ ABSOLUTE MAXIMUM RATINGS AT TA=25°C

PARAMETER	SYMBOL	RATINGS	UNIT
Supply Voltage	V ⁺	12	V
Total Power Dissipation	P _D	700	mW
Operating Temperature Range	T _{opr}	-40~+85	°C
Storage Temperature Range	T _{stg}	-40~+125	°C

■ ELECTRICAL CHARACTERISTICS

(Ta=25°C, all levels reference to -6dBm/400Hz at DOLBY OUT NR OFF, Unless otherwise specified.)

□ SUPPLY

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Operating Voltage Range	V _{op}		8	8.5	10.5	V
Operating Current	I _s		—	18	25	mA
Reference Voltage	V _{ref}		4.0	4.3	4.6	V
DC Voltage Pin 14	V _{dc}		1.15	1.25	1.35	V
MUTE ON LEVEL	MUTE ON		0	—	1.2	V
MUTE OFF LEVEL	MUTE OFF		2.2	—	V ⁺	V
MUTE	ATT		55	65	—	dB
MUTE Current	IMUTE		—	10	—	μA

□ PREAMPLIFIER

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Input Resistance	R _i		30	50	70	kΩ
Input Bias Current	I _i		—	—	10	μA
Voltage Gain	G _v	pin4~5 and 26~27 shorted	32.5	35.5	38.5	dB
Voltage Gain Matching	ΔG _v		-1	—	1	dB
Resistor Metal Position	R _m		4.35	5.8	7.25	kΩ
Resistor Normal Position	R _n		—	150	400	kΩ
Total Input Noise	en 1	R _g =600Ω B=20~20kHz	—	0.8	—	μV
	en 2	R _g =600Ω, A-Weight	—	0.5	—	μV
Forward/Rev. Low Level	FRL	IN 2=ON; IN 1=OFF	0	—	0.8	V
Forward/Rev. High Level	FRH	IN 2=OFF; IN 1=ON	2	—	V ⁺	V
Metal/Normal Low Level	NML	EQSW=ON	0	—	1.5	V
Metal/Normal High Level	NMH	EQSW=OFF	3.5	—	V ⁺	V
Output Impedance	R _o		—	1.2	1.7	Ω

□ AUDIO MUSIC SENSOR

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Output Low Level Voltage	V _l		—	—	800	mV
Input Current	I _{in}		—	—	1	μA
ON/OFF Low level	AMSL		—	—	0.8	V
ON/OFF High Level	ANSH		2	—	V ⁺	V
Interprogram Threshold Voltage	VTH 1		1.2	1.45	1.7	V
Interspace Threshold Voltage	VTH 2		4.0	4.3	4.6	V
AMS Threshold	AMSVTH 1		1.19	1.39	1.59	V
	AMSVTH 2		0.6	0.8	1.0	V
Switch Pin Current	Vol		—	18	—	μA

DOLBY SECTION

PARAMETER	SYMBOL	TEST CONDITION			MIN.	TYP.	MAX.	UNIT
		NR	f(Hz)	OTHER CONDITIONS				
Voltage Gain	G _v	OFF	1K		-1	0	1	dB
Channel Matching	ΔG _v	OFF	1K		-0.5	—	0.5	dB
Signal Handling	S/H	ON	1K	V _{CC} =8V, THD=1%	12	13	—	dB
Decode Cut	B-DEC1	ON	10K	V _{out} =0dB	-1.1	0.4	1.9	dB
	B-DEC2	ON	500	V _{out} =-25dB	1.4	2.9	4.4	dB
20log $\frac{V_{out}(off)}{V_{out}(on)}$	B-DEC3	ON	2K	V _{out} =-25dB	5.5	7.0	8.5	dB
	B-DEC4	ON	5K	V _{out} =-25dB	3.9	5.4	6.9	dB
	B-DEC5	ON	10K	V _{out} =-40dB	8.9	10.4	11.9	dB
ON/OFF Low Level	NR _{off}				0	—	0.8	V
ON/OFF High Level	NR _{on}				2.0	—	V+	V

GENERAL

PARAMETER	SYMBOL	TEST CONDITION			MIN.	TYP.	MAX.	UNIT
		NR	f(Hz)	OTHER CONDITIONS				
Total Harmonics Distortion	THD1	OFF	1K	V _O =0dB	—	0.12	—	%
	THD2	ON	1K	V _O =0dB	—	0.08	—	%
	THD3	OFF	10K	V _O =0dB	—	0.18	—	%
	THD4	ON	10K	V _O =0dB	—	0.2	—	%
Signal to Noise Ratio	S/N1	OFF		R _g =600Ω, V _O =0dB	—	60	—	dB
	S/N2	ON		CCIR/ARM	—	70	—	dB
Channel Separation	CS1	OFF	1K	R _g =600Ω	—	55	—	dB
	CS2	ON	1K	R _g =600Ω	—	60	—	dB
Channel Cross Talk	CT1	OFF	1K	R _g =600Ω	—	58	—	dB
	CT2	ON	1K	R _g =600Ω	—	67	—	dB
Supply Voltage Rejection	SVR1	OFF	1K	R _g =600Ω	—	90	—	dB
	SVR2	ON	1K	R _g =600Ω	—	95	—	dB

5

MEMO

[CAUTION]

The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.

SUNSTAR 商斯达实业集团是集研发、生产、工程、销售、代理经销、技术咨询、信息服务等为一体的高科技企业，是专业高科技电子产品生产厂家，是具有 10 多年历史的专业电子元器件供应商，是中国最早和最大的仓储式连锁规模经营大型综合电子零部件代理分销商之一，是一家专业代理和分销世界各大品牌 IC 芯片和电子元器件的连锁经营综合性国际公司，专业经营进口、国产名厂名牌电子元件，型号、种类齐全。在香港、北京、深圳、上海、西安、成都等全国主要电子市场设有直属分公司和产品展示展销窗口门市部专卖店及代理分销商，已在全国范围内建成强大统一的供货和代理分销网络。我们专业代理经销、开发生产电子元器件、集成电路、传感器、微波光电元器件、工控机/DOC/DOM 电子盘、专用电路、单片机开发、MCU/DSP/ARM/FPGA 软件硬件、二极管、三极管、模块等，是您可靠的一站式现货配套供应商、方案提供商、部件功能模块开发配套商。商斯达实业公司拥有庞大的资料库，有数位毕业于著名高校——有中国电子工业摇篮之称的西安电子科技大学（西军电）并长期从事国防尖端科技研究的高级工程师为您精挑细选、量身订做各种高科技电子元器件，并解决各种技术问题。

微波光电部专业代理经销高频、微波、光纤、光电元器件、组件、部件、模块、整机；电磁兼容元器件、材料、设备；微波 CAD、EDA 软件、开发测试仿真工具；微波、光纤仪器仪表。欢迎国外高科技微波、光纤厂商将优秀产品介绍到中国、共同开拓市场。长期大量现货专业批发高频、微波、卫星、光纤、电视、CATV 器件：晶振、VCO、连接器、PIN 开关、变容二极管、开关二极管、低噪晶体管、功率电阻及电容、放大器、功率管、MMIC、混频器、耦合器、功分器、振荡器、合成器、衰减器、滤波器、隔离器、环行器、移相器、调制解调器；光电子元件和组件：红外发射管、红外接收管、光电开关、光敏管、发光二极管和发光二极管组件、半导体激光二极管和激光器组件、光电探测器和光接收组件、光发射接收模块、光纤激光器和光放大器、光调制器、光开关、DWDM 用光发射和接收器件、用户接入系统光收发器件与模块、光纤连接器、光纤跳线/尾纤、光衰减器、光纤适配器、光隔离器、光耦合器、光环行器、光复用器/转换器；无线收发芯片和模组、蓝牙芯片和模组。

更多产品请看本公司产品专用销售网站：

商斯达中国传感器科技信息网：<http://www.sensor-ic.com/>

商斯达工控安防网：<http://www.pc-ps.net/>

商斯达电子元器件网：<http://www.sunstare.com/>

商斯达微波光电产品网：[HTTP://www.rfoe.net/](http://www.rfoe.net/)

商斯达消费电子产品网：<http://www.icasic.com/>

商斯达实业科技产品网：<http://www.sunstars.cn/> 微波元器件销售热线：

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-82884100 83397033 83396822 83398585

传真：0755-83376182 (0) 13823648918 MSN: SUNS8888@hotmail.com

邮编：518033 E-mail:szss20@163.com QQ: 195847376

深圳赛格展销部：深圳华强北路赛格电子市场 2583 号 电话：0755-83665529 25059422

技术支持：0755-83394033 13501568376

欢迎索取免费详细资料、设计指南和光盘；产品凡多，未能尽录，欢迎来电查询。

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL: 010-81159046 82615020 13501189838 FAX: 010-62543996

上海分公司：上海市北京东路 668 号上海赛格电子市场 D125 号

TEL: 021-28311762 56703037 13701955389 FAX: 021-56703037

西安分公司：西安高新开发区 20 所(中国电子科技集团导航技术研究所)

西安劳动南路 88 号电子商城二楼 D23 号

TEL: 029-81022619 13072977981 FAX:029-88789382