

# DATA SHEET

**BLF277**  
VHF power MOS transistor

Product specification

September 1992

**VHF power MOS transistor****BLF277****FEATURES**

- High power gain
- Easy power control
- Gold metallization ensures excellent reliability
- Good thermal stability
- Withstands full load mismatch.

**DESCRIPTION**

Silicon N-channel enhancement mode vertical D-MOS transistor designed for large signal amplifier applications in the VHF frequency range.

The transistor is encapsulated in a 6-lead, SOT119 flange envelope, with a ceramic cap. All leads are isolated from the flange.

A marking code, showing gate-source voltage ( $V_{GS}$ ) information is provided for matched pair applications. Refer to the 'General' section for further information.

**PINNING - SOT119**

PIN	DESCRIPTION
1	source
2	source
3	gate
4	drain
5	source
6	source


**PIN CONFIGURATION**

Fig.1 Simplified outline and symbol.

**CAUTION**

The device is supplied in an antistatic package. The gate-source input must be protected against static charge during transport and handling.

**WARNING****Product and environmental safety - toxic materials**

This product contains beryllium oxide. The product is entirely safe provided that the BeO disc is not damaged. All persons who handle, use or dispose of this product should be aware of its nature and of the necessary safety precautions. After use, dispose of as chemical or special waste according to the regulations applying at the location of the user. It must never be thrown out with the general or domestic waste.

**QUICK REFERENCE DATA**

RF performance at  $T_h = 25^\circ\text{C}$  in a common source circuit.

MODE OF OPERATION	f (MHz)	$V_{DS}$ (V)	$P_L$ (W)	$G_p$ (dB)	$\eta_D$ (%)
CW, class-B	175	50	150	> 14	> 50

## VHF power MOS transistor

BLF277


**LIMITING VALUES**

In accordance with the Absolute Maximum System (IEC 134).

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.	UNIT
$V_{DS}$	drain-source voltage		–	110	V
$\pm V_{GS}$	gate-source voltage		–	20	V
$I_D$	DC drain current		–	16	A
$P_{tot}$	total power dissipation	up to $T_{mb} = 25^\circ\text{C}$	–	220	W
$T_{stg}$	storage temperature		–65	150	$^\circ\text{C}$
$T_j$	junction temperature		–	200	$^\circ\text{C}$


**THERMAL RESISTANCE**

SYMBOL	PARAMETER	CONDITIONS	THERMAL RESISTANCE
$R_{th\ j-mb}$	thermal resistance from junction to mounting base	$T_{mb} = 25^\circ\text{C}; P_{tot} = 220\text{ W}$	0.8 K/W
$R_{th\ mb-h}$	thermal resistance from mounting base to heatsink	$T_{mb} = 25^\circ\text{C}; P_{tot} = 220\text{ W}$	0.2 K/W



- (1) Current in this area may be limited by  $R_{DS(on)}$ .  
(2)  $T_{mb} = 25^\circ\text{C}$ .

Fig.2 DC SOAR.



- (1) Continuous operation.  
(2) Short-time operation during mismatch.

Fig.3 Power/temperature derating curves.



## VHF power MOS transistor

BLF277

## CHARACTERISTICS

 $T_j = 25^\circ\text{C}$  unless otherwise specified.

SYMBOL	PARAMETER	CONDITIONS	MIN.	TYP.	MAX.	UNIT
$V_{(\text{BR})\text{DSS}}$	drain-source breakdown voltage	$V_{\text{GS}} = 0$ ; $I_D = 50 \text{ mA}$	110	—	—	V
$I_{\text{DSS}}$	drain-source leakage current	$V_{\text{GS}} = 0$ ; $V_{\text{DS}} = 50 \text{ V}$	—	—	2.5	mA
$I_{\text{GSS}}$	gate-source leakage current	$\pm V_{\text{GS}} = 20 \text{ V}$ ; $V_{\text{DS}} = 0$	—	—	1	$\mu\text{A}$
$V_{\text{GS}(\text{th})}$	gate-source threshold voltage	$I_D = 50 \text{ mA}$ ; $V_{\text{DS}} = 10 \text{ V}$	2	—	4.5	V
$\Delta V_{\text{GS}}$	gate-source voltage difference of matched pairs	$I_D = 50 \text{ mA}$ ; $V_{\text{DS}} = 10 \text{ V}$	—	—	100	mV
$g_{\text{fs}}$	forward transconductance	$I_D = 5 \text{ A}$ ; $V_{\text{DS}} = 10 \text{ V}$	4.5	6.2	—	S
$R_{\text{DS}(\text{on})}$	drain-source on-state resistance	$I_D = 5 \text{ A}$ ; $V_{\text{GS}} = 10 \text{ V}$	—	0.2	0.3	$\Omega$
$I_{\text{DSX}}$	on-state drain current	$V_{\text{GS}} = 10 \text{ V}$ ; $V_{\text{DS}} = 10 \text{ V}$	—	25	—	A
$C_{\text{is}}$	input capacitance	$V_{\text{GS}} = 0$ ; $V_{\text{DS}} = 50 \text{ V}$ ; $f = 1 \text{ MHz}$	—	480	—	pF
$C_{\text{os}}$	output capacitance	$V_{\text{GS}} = 0$ ; $V_{\text{DS}} = 50 \text{ V}$ ; $f = 1 \text{ MHz}$	—	190	—	pF
$C_{\text{rs}}$	feedback capacitance	$V_{\text{GS}} = 0$ ; $V_{\text{DS}} = 50 \text{ V}$ ; $f = 1 \text{ MHz}$	—	14	—	pF



## VHF power MOS transistor

BLF277


 $I_D = 5 \text{ A}; V_{GS} = 10 \text{ V}.$ 

Fig.6 Drain-source on-state resistance as a function of junction temperature, typical values.


 $V_{GS} = 0; f = 1 \text{ MHz}.$ 

Fig.7 Input and output capacitance as functions of drain-source voltage, typical values.


 $V_{GS} = 0; f = 1 \text{ MHz}.$ 

Fig.8 Feedback capacitance as a function of drain-source voltage, typical values.

## VHF power MOS transistor

BLF277

## APPLICATION INFORMATION FOR CLASS-B OPERATION

 $T_h = 25^\circ\text{C}$ ;  $R_{th\text{ mb-h}} = 0.2 \text{ K/W}$ ;  $R_{GS} = 16 \Omega$ ; unless otherwise specified.



RF performance in CW operation in a common source class-B test circuit.

MODE OF OPERATION	f (MHz)	V <sub>DS</sub> (V)	I <sub>DQ</sub> (A)	P <sub>L</sub> (W)	G <sub>p</sub> (dB)	η <sub>D</sub> (%)
CW, class-B	175	50	0.1	150	> 14 typ. 17	> 50 typ. 58

## Ruggedness in class-B operation

The BLF277 is capable of withstanding a load mismatch corresponding to VSWR = 50 through all phases under the following conditions:

$V_{DS} = 50 \text{ V}$ ;  $f = 175 \text{ MHz}$  at rated load power.



## VHF power MOS transistor

BLF277




Fig.11 Test circuit for class-B operation.

## VHF power MOS transistor

BLF277

## List of components (class-B test circuit)

COMPONENT	DESCRIPTION	VALUE	DIMENSIONS	CATALOGUE NO.
C1, C8, C19	multilayer ceramic chip capacitor (note 1)	680 pF		
C2, C4, C17	film dielectric trimmer	5 to 60 pF		2222 809 08003
C3	multilayer ceramic chip capacitor (note 1)	33 pF		
C5, C6, C9	multilayer ceramic chip capacitor (note 1)	100 pF		
C7, C10, C13	multilayer ceramic chip capacitor	100 nF		2222 852 47104
C11	multilayer ceramic chip capacitor	10 nF		2222 852 47103
C12	electrolytic capacitor	10 µF, 63 V		
C14, C15	multilayer ceramic chip capacitor (note 2)	3 × 22 pF in parallel		
C16	film dielectric trimmer	4 to 40 pF		2222 809 08002
C18	multilayer ceramic chip capacitor (note 1)	18 pF		
L1	stripline (note 3)	49 Ω	length 8 mm width 4 mm	
L2	stripline (note 3)	49 Ω	length 12 mm width 4 mm	
L3	stripline (note 3)	49 Ω	length 7.5 mm width 4 mm	
L4	2 turns enamelled 1.5 mm copper wire	25 nH	length 3.7 mm int. dia. 5 mm leads 2 × 1 mm	
L5	stripline (note 3)	49 Ω	length 15.5 mm width 4 mm	
L6	stripline (note 3)	49 Ω	length 5 mm width 4 mm	
L7	2 turns enamelled 1.5 mm copper wire	25 nH	length 4.2 mm int. dia. 5 mm leads 2 × 4 mm	
L8	stripline (note 3)	31 Ω	length 18 mm width 6 mm	
L9	stripline (note 3)	31 Ω	length 6 mm width 6 mm	
L10, L12	stripline (note 3)	31 Ω	length 7 mm width 6 mm	
L11	3 turns enamelled 1.5 mm copper wire	40 nH	length 6.8 mm int. dia. 5 mm leads 2 × 3 mm	
L13	1 turn enamelled 1.5 mm copper wire	3 nH	int. dia. 2.8 mm leads 2 × 1 mm	
L14	stripline (note 3)	36 Ω	length 15.5 mm width 5 mm	

## VHF power MOS transistor

BLF277



COMPONENT	DESCRIPTION	VALUE	DIMENSIONS	CATALOGUE NO.
L15	stripline (note 3)	36 Ω	length 8 mm width 5 mm	
L16	2 turns enamelled 2.5 mm copper wire	28 nH	length 5.5 mm int. dia. 5 mm leads 2 × 3 mm	
L17	stripline (note 3)	36 Ω	length 12 mm width 5 mm	
L18, L19	stripline (note 3)	36 Ω	length 8.5 mm width 5 mm	
L20	grade 3B Ferroxcube RF choke			4312 020 36642
R1	0.4 W metal film resistor	16 Ω		
R2	10 turn potentiometer	50 kΩ		
R3	0.4 W metal film resistor	400 kΩ		
R4	0.4 W metal film resistor	100 kΩ		

**Notes**

1. American Technical Ceramics (ATC) capacitor, type 100B or other capacitor of the same quality.
2. American Technical Ceramics (ATC) capacitor, type 175B or other capacitor of the same quality.
3. The striplines are mounted double copper-clad printed circuit board, with epoxy glass dielectric ( $\epsilon_r = 4.5$ ); thickness 1.6 mm.

## VHF power MOS transistor

BLF277




The circuit and components are situated on one side of the printed circuit board, the other side being fully metallized, to serve as a ground plane. Earth connections are made by means of copper straps and hollow rivets.

Fig.12 Component layout for 175 MHz class-B test circuit.


## VHF power MOS transistor

BLF277



Class-B operation;  $V_{DS} = 50$  V;  $I_{DQ} = 0.1$  A;  
 $R_{GS} = 16 \Omega$ ;  $P_L = 150$  W.

Fig.13 Input impedance as a function of frequency (series components), typical values.



Class-B operation;  $V_{DS} = 50$  V;  $I_{DQ} = 0.1$  A;  
 $R_{GS} = 16 \Omega$ ;  $P_L = 150$  W.

Fig.14 Load impedance as a function of frequency (series components), typical values.





Fig.15 Definition of MOS impedance.



Class-B operation;  $V_{DS} = 50$  V;  $I_{DQ} = 0.1$  A;  
 $R_{GS} = 16 \Omega$ ;  $P_L = 150$  W.

Fig.16 Power gain as a function of frequency, typical values.


## VHF power MOS transistor

BLF277

## PACKAGE OUTLINE

Flanged ceramic package; 2 mounting holes; 6 leads

SOT119A



DIMENSIONS (millimetre dimensions are derived from the original inch dimensions)

UNIT	A	b	b <sub>1</sub>	b <sub>2</sub>	c	D	D <sub>1</sub>	e	F	H	H <sub>1</sub>	p	Q	q	U <sub>1</sub>	U <sub>2</sub>	U <sub>3</sub>	w <sub>1</sub>	w <sub>2</sub>	w <sub>3</sub>
mm	7.39 6.32	5.59 5.33	5.34 5.08	4.07 3.81	0.18 0.07	12.86 12.59	12.83 12.57	6.48	2.54 2.28	22.10 21.08	18.55 18.28	3.31 2.97	4.58 3.98	18.42	25.23 23.95	6.48 6.07	12.76 12.06	0.51	1.02	0.26
inches	0.291 0.249	0.220 0.210	0.210 0.200	0.160 0.150	0.007 0.003	0.505 0.496	0.505 0.495	0.255	0.100 0.090	0.870 0.830	0.730 0.720	0.130 0.117	0.180 0.157	0.725	0.993 0.943	0.255 0.239	0.502 0.475	0.02	0.04	0.01

OUTLINE VERSION	REFERENCES				EUROPEAN PROJECTION	ISSUE DATE
	IEC	JEDEC	EIAJ			
SOT119A						97-06-28

**VHF power MOS transistor****BLF277****DEFINITIONS**

<b>Data Sheet Status</b>	
Objective specification	This data sheet contains target or goal specifications for product development.
Preliminary specification	This data sheet contains preliminary data; supplementary data may be published later.
Product specification	This data sheet contains final product specifications.
<b>Limiting values</b>	
Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.	
<b>Application information</b>	
Where application information is given, it is advisory and does not form part of the specification.	

**LIFE SUPPORT APPLICATIONS**

These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips for any damages resulting from such improper use or sale.

SUNSTAR 商斯达实业集团是集研发、生产、工程、销售、代理经销、技术咨询、信息服务等为一体的高科技企业，是专业高科技电子产品生产厂家，是具有 10 多年历史的专业电子元器件供应商，是中国最早和最大的仓储式连锁规模经营大型综合电子零部件代理分销商之一，是一家专业代理和分销世界各大品牌 IC 芯片和电子元器件的连锁经营综合性国际公司，专业经营进口、国产名厂名牌电子元件，型号、种类齐全。在香港、北京、深圳、上海、西安、成都等全国主要电子市场设有直属分公司和产品展示展销窗口门市部专卖店及代理分销商，已在全国范围内建成强大统一的供货和代理分销网络。我们专业代理经销、开发生产电子元器件、集成电路、传感器、微波光电元器件、工控机/DOC/DOM 电子盘、专用电路、单片机开发、MCU/DSP/ARM/FPGA 软件硬件、二极管、三极管、模块等，是您可靠的一站式现货配套供应商、方案提供商、部件功能模块开发配套商。商斯达实业公司拥有庞大的资料库，有数位毕业于著名高校——有中国电子工业摇篮之称的西安电子科技大学（西军电）并长期从事国防尖端科技研究的高级工程师为您精挑细选、量身订做各种高科技电子元器件，并解决各种技术问题。

微波光电部专业代理经销高频、微波、光纤、光电元器件、组件、部件、模块、整机；电磁兼容元器件、材料、设备；微波 CAD、EDA 软件、开发测试仿真工具；微波、光纤仪器仪表。欢迎国外高科技微波、光纤厂商将优秀产品介绍到中国、共同开拓市场。长期大量现货专业批发高频、微波、卫星、光纤、电视、CATV 器件：晶振、VCO、连接器、PIN 开关、变容二极管、开关二极管、低噪晶体管、功率电阻及电容、放大器、功率管、MMIC、混频器、耦合器、功分器、振荡器、合成器、衰减器、滤波器、隔离器、环行器、移相器、调制解调器；光电子元器件和组件：红外发射管、红外接收管、光电开关、光敏管、发光二极管和发光二极管组件、半导体激光二极管和激光器组件、光电探测器和光接收组件、光发射接收模块、光纤激光器和光放大器、光调制器、光开关、DWDM 用光发射和接收器件、用户接入系统光光收发器件与模块、光纤连接器、光纤跳线/尾纤、光衰减器、光纤适配器、光隔离器、光耦合器、光环行器、光复用器/转换器；无线收发芯片和模组、蓝牙芯片和模组。

更多产品请看本公司产品专用销售网站：

商斯达中国传感器科技信息网：<http://www.sensor-ic.com/>

商斯达工控安防网：<http://www.pc-ps.net/>

商斯达电子元器件网：<http://www.sunstare.com/>

商斯达微波光电产品网：<HTTP://www.rfoe.net/>

商斯达消费电子产品网：<http://www.icasic.com/>

商斯达实业科技产品网：<http://www.sunstars.cn/> 微波元器件销售热线：

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-82884100 83397033 83396822 83398585

传真：0755-83376182 (0) 13823648918 MSN：[SUNS8888@hotmail.com](mailto:SUNS8888@hotmail.com)

邮编：518033 E-mail：[szss20@163.com](mailto:szss20@163.com) QQ：195847376

深圳赛格展销部：深圳华强北路赛格电子市场 2583 号 电话：0755-83665529 25059422

技术支持：0755-83394033 13501568376

欢迎索取免费详细资料、设计指南和光盘；产品凡多，未能尽录，欢迎来电查询。

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL：010-81159046 82615020 13501189838 FAX：010-62543996

上海分公司：上海市北京东路 668 号上海赛格电子市场 D125 号

TEL：021-28311762 56703037 13701955389 FAX：021-56703037

西安分公司：西安高新区 20 所(中国电子科技集团导航技术研究所)

西安劳动南路 88 号电子商城二楼 D23 号

TEL：029-81022619 13072977981 FAX:029-88789382