SUNSTAR传感与控制 http://www.sensor-ic.com/ TEL:0755-83376549 FAX:0755-83376182 E-MAIL:szss20@163.com

Nitric Oxide CiTiceL[®] Specification



6.5

) DCB

MOLEX CONNECTOR

Outline Dimensions

Ø31.6

SEN\$OR

Ø34.6 APPROX

VIEW FROM ABOVE

(+V)

(- V)

(V out)

(Common)

PIN CONFIGURATION OF AUTO NO NX1 SENSOR

Red

Green

Black

Yellow

M16 X 1 PITCH

41.4mm APPROX

7mm APPROX

3V BATTERY (Ø14mm APPROX)

1

2

3 🗌

4

NX1 CiTiceL[®] (Rev 4)

For BAR 97 grade markets

Performance Characteristics

Nominal Range	0-5000ppm
Inboard Filter	To remove effect of SO_2 in gas stream
Output Signal	0.05 ± 0.01 μA/ppm
Resolution	1ppm
Temperature Range	-20°C to +50°C
Pressure Range	800 to 1100 mBar
Pressure Coefficient	0.02% signal/mBar
T ₉₅ Response Time*	≤5.5 seconds
T ₉₀ Response Time*	≤4.5 seconds
Relative Humidity Range	15 to 90% non-condensing
Typical Baseline Range (pure air)	0 to +12ppm equivalent
Maximum Zero Shift (0°C to +40°C)	<30ppm equivalent
Long Term Output Drift	Typically <5% signal loss/year
Recommended Load Resistor	10 Ω
Bias Voltage	+300mV
Repeatability	2% of signal
Output Linearity	Linear

* Prolonged exposure to high or low humidity may lead to an increased Response Time

N.B. All performance data is based on conditions at 20°C, 50%RH, and 1013mBar

Physical Characteristics




Doc. Ref.: nx1rev4.pmd Issue 1.7

Page 1 of 2

2nd July 2003


City Technology Ltd, City Technology Centre, Walton Rd, Portsmouth PO6 1SZ, UK Tel:+44 23 9232 5511, Fax:+44 23 9238 6611, sensors@citytech.co.uk, www.citytech.com SUNSTAR自动化 http://www.sensor-ic.com/ TEL: 0755-83376489 FAX:0755-83376182 E-MAIL:szss20@163.com

Nitric Oxide CiTiceL[®] Specification



Recommended External Circuit for Sensor

This diagram shows the recommended operating circuit for the NX1 CiTiceL, designed to give an output of 0-5V over the range 0-5000ppm, where the sensitivity is 60nA/ppm.



Every effort has been made to ensure the accuracy of this document at the time of printing. In accordance with the company's policy of continued product improvement City Technology Limited reserves the right to make product changes without notice. No liability is accepted for any consequential losses, injury or damage resulting from the use of this document or from any omissions or errors herein. The data is given for guidance only. It does not constitute a specification or an offer for sale. The products are always subject to a programme of improvement and testing which may result in some changes in the characteristics quoted. As the products may be used by the client in circumstances beyond the knowledge and control of City Technology Limited, we cannot give any warranty as to the relevance of these particulars to an application. It is the clients' responsibility to carry out the necessary tests to determine the usefulness of the products and to ensure their safety of operation in a particular application.

Performance characteristics on this data sheet outline the performance of newly supplied sensors. Output signal can drift below the lower limit over time.

Doc. Ref.: nx1rev4.pmd Issue 1.7

Page 2 of 2

2nd July 2003

City Technology Ltd, City Technology Centre, Walton Rd, Portsmouth PO6 1SZ, UK Tel:+44 23 9232 5511, Fax:+44 23 9238 6611, sensors@citytech.co.uk, www.citytech.com SUNSTAR自动化 http://www.sensor-ic.com/ TEL: 0755-83376489 FAX:0755-83376182 E-MAIL:szss20@163.com